


RSA SecurID Access HFED Proxy Configuration for BugHost




Last Modified: August 30, 2016

BugHost is an easy-to-use bug and issue tracking system for all types of projects - from small business apps to enterprise-wide systems.

Before You Begin

 **Note:** Before proceeding with this HFED guide, look to see if a SAML guide is available.

- Acquire an RSA SecurID Access administrator account.
- Acquire a BugHost account.
- Configure DNS canonical names (CNAMEs) or aliases for the protected hostnames to the identity router. For example, *appname-resources.sso.example.com* is a CNAME to *portal.sso.example.com*.

 **Note:** You can use a wildcard CNAME to add HFED an application-protected hostname without creating individual DNS entries. For example:

**.sso.example.com* is a CNAME to *portal.sso.example.com*


Procedure

1. [Add the Application in RSA SecurID Access](#)
2. [Configure BugHost to Use RSA SecurID Access as an Identity Provider](#)

Add the Application in RSA SecurID Access

Procedure

1. Log in to the RSA SecurID Access Administration Console, click the **Applications** tab and select *Application Catalog* from the **Application** tab dropdown list.



2. Search for *BugHost* in the list of applications and click the **+Add** button.





3. Enter a name for the application in the **Name** field on the **Basic Information** page and click the **Next Step** button.
4. Verify that the values in the **Logon Form URL** field and **Web Servers** table on the **Branded Setting** page match the values below.

Branded Settings

Logon Form URL ?

 Pass Attributes Pass Headers Verify Certificates

Web Servers

| Protocol | Proxy Hostname | Real Hostname | |
|--------------------|---------------------------------|-----------------|---|
| ANY | www-bughost-com.sso3.pe-lab.com | www.bughost.com |   |
| + ADD | | | |

5. Click the **Next Step** button.
6. On the **User Access** page, select the access policy the identity router will use to determine which users can access the BugHost application from the portal. If you want to allow access to all users who are signed into the portal, select the **Allow All Authenticated Users** radio button. Otherwise, select the **Select Custom Policy** radio button and select the policy you want to use from the dropdown list.

Allow All Authenticated Users
 Select Custom Policy ?

No Access Allowed ▼

7. Click the **Next Step** button.

8. Select the **Display in Portal** checkbox on the **Portal Display** page.

Specify how the application appears in the application portal.

Display in Portal ?

Application Icon

Image file must be JPG or PNG format,
and no larger than 50 KB.
The recommended size is 75x75 pixels.



Change Icon

9. Enter descriptive text about the application in the **Application Tooltip** field. The portal will display this text when a user passes the cursor over the application's icon.
10. If you want to allow users to change their BugHost credentials in the portal, check **Allow Users to Change Credentials**.
11. Click the **Save and Finish** button.

Application Tooltip ?

BugHost

Portal URL ?


https://www-bughost-com.sso3.pe-lab.com/proUI/TimezoneSetForm.asp

Allow Users to Change Credentials ?

Cancel

Save and Finish

12. Click the **Publish Changes** button in the top left corner of the page.

Publish Changes Status:  Changes Pending

Configure BugHost to Use RSA SecurID Access as an Identity Provider

There are no necessary BugHost-side configuration changes to enable integration with RSA SecurID Access.