



RSA Identity Governance and Lifecycle Upgrade and Migration Guide

Version 7.2

Revision 1

Contact Information

RSA Link at <https://community.rsa.com> contains a knowledgebase that answers common questions and provides solutions to known problems, product documentation, community discussions, and case management.

Trademarks

Dell, RSA, the RSA Logo, EMC and other trademarks, are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners. For a list of RSA trademarks, go to www.emc.com/legal/emc-corporation-trademarks.htm#rsa.

License agreement

This software and the associated documentation are proprietary and confidential to Dell Inc. or its subsidiaries, are furnished under license, and may be used and copied only in accordance with the terms of such license and with the inclusion of the copyright notice below. This software and the documentation, and any copies thereof, may not be provided or otherwise made available to any other person.

No title to or ownership of the software or documentation or any intellectual property rights thereto is hereby transferred. Any unauthorized use or reproduction of this software and the documentation may be subject to civil and/or criminal liability.

This software is subject to change without notice and should not be construed as a commitment by Dell Inc.

Third-party licenses

This product may include software developed by parties other than RSA. The text of the license agreements applicable to third-party software in this product may be viewed by launching the RSA Identity Governance and Lifecycle product and selecting the About menu. By using this product, a user of this product agrees to be fully bound by terms of the license agreements.

Note on encryption technologies

This product may contain encryption technology. Many countries prohibit or restrict the use, import, or export of encryption technologies, and current use, import, and export regulations should be followed when using, importing or exporting this product.

Distribution

Use, copying, and distribution of any Dell software described in this publication requires an applicable software license.

Dell Inc. believes the information in this publication is accurate as of its publication date. The information is subject to change without notice.

THE INFORMATION IN THIS PUBLICATION IS PROVIDED "AS IS." DELL INC. MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WITH RESPECT TO THE INFORMATION IN THIS PUBLICATION, AND SPECIFICALLY DISCLAIMS IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

Copyright © 2020 Dell Inc. or its subsidiaries. All Rights Reserved.

February 2020

February 2020

Contents

Preface	6
About This Guide	6
Documentation Set	6
Support and Service	6
Revision History	7
Chapter 1: Supported Upgrade Scenarios	8
Chapter 2: Pre-Upgrade Tasks for Migrating Collectors	10
Changes to Data Collections	10
About Full Refresh Collections after Migration	10
Migration Reports	10
The Migration Report Utility	12
Download the Migration Report Utility	12
Install the Migration Reports	13
Run the Full Migration Report	14
Upgrade on WebLogic or WebSphere hosted on AIX	15
Run an Individual Migration Report	15
Chapter 3: Pre-Upgrade Tasks for Migrating Group Business Descriptions	18
Unused Group Business Descriptions Not Associated with an Application	18
All Unused Group Business Descriptions	19
Group Business Description Table	20
Chapter 4: Verify Upgrade Prerequisites	22
Review Public Database Schema and Port Changes Introduced in v7.0.1	22
Database Schema Changes	22
Port Changes	22
Verify Prerequisites for an RSA Appliance	23
Verify Prerequisites for a Software Bundle Upgrade	23
Verify Prerequisites for a Virtual Application	24
Verify Prerequisites for WebSphere	25
Verify Prerequisites for WebLogic	25
Chapter 5: Prepare to Upgrade the RSA Identity Governance and Lifecycle Software	28
Back up the RSA Identity Governance and Lifecycle Application	28

Apply the Latest Operating System and Database Patch Updates	29
Back Up the RSA-Supplied Database	29
Back Up the Customer-Supplied Database	30
Prepare for an Upgrade on WebLogic	31
Prepare for an Upgrade on WebSphere	31
Chapter 6: Perform the Upgrade	32
Upgrade RSA Identity Governance and Lifecycle on an Appliance or Software Bundle Server	32
Download the RSA Identity Governance and Lifecycle Installation Files	32
Copy the Installation Files to the Installation Host	33
Run the Installation Script	34
Verify the Upgrade Succeeded (RSA-Supplied Database)	35
Verify Data Restoration and Start All Services	36
Confirm the Setting for the Encryption Key Directory	36
Using Non-restrictive Mode for the Encryption Key Directory	38
Error Messages	39
Re-install Remote Agents	40
Restore Your Customization Files	40
Delete the Jboss Folder (When Upgrading From a Pre-v7.0 Product Version)	41
Upgrade RSA Identity Governance and Lifecycle on WebSphere Application Server	41
Update the ACM Oracle JDBC Provider	42
Update the AVDWDB Data Source in WebSphere	42
Deploy the WebSphere Installation EAR Files	42
Configure the RSA Identity Governance and Lifecycle Shared Library	44
Update the Setting for the Encryption Key Directory	45
Using Non-restrictive Mode for the Encryption Key Directory	46
Error Messages	47
Upgrade RSA Identity Governance and Lifecycle on WebLogic Application Server	48
Update the AVDWDB Data Source in WebLogic	48
Deploy the WebLogic Installation EAR Files	49
Update the Setting for the Encryption Key Directory	50
Using Non-restrictive Mode for the Encryption Key Directory	51
Error Messages	53
Upgrade AFX	54

Upgrade AFX If You Have a Pre-6.8.1 Version Installed	55
Migrate AFX Connectors and Templates from AFX 2.0.x or 2.5.x	55
Run the AFX Connector Converter Utility	55
Import the Connector and the Connector Template Packages Archives into RSA Identity Governance and Lifecycle v7.x	56
Upgrade the AFX Server to Version 7.x	57
Verify the Upgrade	57
Update Keystores	58
Chapter 7: Upgrade or Migrate to an RSA Identity Governance and Lifecycle Virtual Application	60
Download and Install the RSA Identity Governance and Lifecycle Virtual Application OVA	60
Set Up the Database for the Virtual Application	61
Set Up the RSA Identity Governance and Lifecycle Virtual Application	61
Restore the RSA Identity Governance and Lifecycle Deployment	63

Preface

About This Guide

This guide provides instructions for upgrading RSA Identity Governance and Lifecycle software. It is intended for administrators and other trusted personnel.

This guide describes the process of upgrading to a new major, minor, or service pack release of RSA Identity Governance and Lifecycle. The procedures in this guide do not apply to installing a patch. For patch installation instructions, see the *RSA Identity Governance and Lifecycle Release Notes*.

Documentation Set

The latest product documentation is always available at <https://community.rsa.com/community/products/governance-and-lifecycle>.

Document	Description
Release Notes	What's new in the release, fixed issues, known issues and workarounds.
Installation Guide	Product installation instructions.
Upgrade and Migration Guide	Instructions for upgrading your product version and data.
Database Setup and Management Guide	Instructions for setting up and managing a customer-supplied Oracle database for RSA Identity Governance and Lifecycle.
Configuring WildFly Clusters	Instructions to set up and configure a WildFly application server cluster in an RSA Identity Governance and Lifecycle deployment.
Online Help	All concepts and instructions you need to configure and use the product.
Administrator's Guide	How to configure and manage RSA Identity Governance and Lifecycle. Contains a subset of the information provided in the Online Help.
Public Database Schema Reference	The public view of the database schema.

Support and Service

You can access community and support information on RSA Link at <https://community.rsa.com/community/products/governance-and-lifecycle>. RSA Link contains a knowledgebase that answers common questions and provides solutions to known problems, product documentation, community discussions, and case management.

You can also access the RSA Identity Governance and Lifecycle community at <https://community.rsa.com/community/products/governance-and-lifecycle/client-partner-community>. This private community is only available to RSA Identity Governance and Lifecycle customers, partners, and internal RSA staff.

Revision History

Revision Number	Date	Revision
1	February 2020	Removed references to obsolete files.

Chapter 1: Supported Upgrade Scenarios

The following table lists supported upgrade scenarios and the tasks you must perform for each.

Scenario	Tasks
Upgrade from v7.0.x on a hardware appliance, software bundle, or software only deployment	<ol style="list-style-type: none"> 1. Verify Upgrade Prerequisites on page 22 2. Prepare to Upgrade the RSA Identity Governance and Lifecycle Software on page 28 3. Perform the Upgrade on page 32
Migrate a Software Bundle to a Virtual Application	<ol style="list-style-type: none"> 1. Verify Upgrade Prerequisites on page 22 2. Prepare to Upgrade the RSA Identity Governance and Lifecycle Software on page 28 3. Upgrade or Migrate to an RSA Identity Governance and Lifecycle Virtual Application on page 60
	<p>Note: To upgrade RSA Identity Governance and Lifecycle in an environment with an existing virtual application, deploy a new OVA running the desired version of RSA Identity Governance and Lifecycle and follow these steps to migrate to the new OVA using the existing database and network details.</p>
Upgrade from product version v6.9.1 on an appliance or compatible server	<ol style="list-style-type: none"> 1. Pre-Upgrade Tasks for Migrating Collectors on page 10 2. Verify Prerequisites for an RSA Appliance on page 23 or Verify Prerequisites for a Software Bundle Upgrade on page 23 3. Prepare to Upgrade the RSA Identity Governance and Lifecycle Software on page 28 4. Upgrade RSA Identity Governance and Lifecycle on an Appliance or Software Bundle Server on page 32
Upgrade from product version v6.9.1 on WebLogic	<ol style="list-style-type: none"> 1. Verify Prerequisites for WebLogic on page 25 2. Back Up the Customer-Supplied Database on page 30 3. Upgrade RSA Identity Governance and Lifecycle on WebLogic Application Server on page 48
Upgrade from product version v6.9.1 on WebSphere	<ol style="list-style-type: none"> 1. Verify Prerequisites for WebSphere on page 25 2. Back Up the Customer-Supplied Database on page 30 3. Upgrade RSA Identity Governance and Lifecycle on WebSphere Application Server on page 41
Upgrade Access Fulfillment Express (AFX)	<ul style="list-style-type: none"> • Upgrade AFX If You Have a Pre-6.8.1 Version Installed on page 55 • Upgrade AFX on page 54 (Software Bundle upgrade scenario) • To initiate the automatic upgrade of AFX during the RSA Identity Governance and Lifecycle upgrade process if AFX is installed on your appliance, see the instructions in Run the Installation Script on page 34.

Note: Existing RSA Identity Governance and Lifecycle Virtual Application deployments are not upgraded within the same OVA. To upgrade RSA Identity Governance and Lifecycle, deploy a new OVA using the instructions described in the RSA Identity Governance and Lifecycle Installation Guide.

Chapter 2: Pre-Upgrade Tasks for Migrating Collectors

Read this chapter only if you are upgrading from a pre-7.0 version of RSA Identity Governance and Lifecycle.

RSA Identity Governance and Lifecycle v7.0.1 and later includes changes that affect the collection of data. For example, Identity Data Collectors (IDCs) no longer collect user group information. Before you upgrade, you must ensure that your existing collectors will continue to run and collect the correct data after you upgrade.

Use the Migration Report Utility to generate reports that list issues related to your current configuration and data and help you resolve those issues. RSA strongly recommends that you use these reports before upgrading. If you do this prior to upgrading, some data might be rejected during migration and you will have to reconfigure some collectors after upgrading.

Changes to Data Collections

RSA Identity Governance and Lifecycle v7.0.1 and later includes the following data collection changes:

- Identity Data Collectors no longer collect user groups.
- Duplicate objects are no longer allowed within an application namespace. Previously, duplicate objects were not allowed within a collector, and as a result more than one collector was allowed to collect the same entitlement for an application.
- Primary Data Access Collectors are no longer able to collect duplicate resources based on the Fully Qualified Name.
- Entitlement Data Collectors no longer collect role entitlements. Instead, Role Data Collectors collect all role entitlements.

About Full Refresh Collections after Migration

When you migrate from a pre-7.0 version of RSA Identity Governance and Lifecycle, note that all of your initial data collections are designated as "full refresh" collections. This means that previously collected data is removed from the system and all data that is collected is new or has changed. All subsequent collections are processed by the delta model.

Migration Reports

After you install and generate the migration reports, you can access the reports from Admin > System > Diagnostics. You can generate all or individual reports that list particular types of issues and the objects affected by those issues. You can download a single HTML version of the reports as you would any other statistics report.

See [The Migration Report Utility on page 12](#) and [Download the Migration Report Utility on page 12](#) for more information.

The following table describes each report and provides the high-level steps required to resolve issues.

Report	Description and Issue Resolution Steps
Active IDC Groups	IDCs no longer collect user groups. If any IDCs collect user groups,

Report	Description and Issue Resolution Steps
	you must reconfigure them.
Collectors Using Identity Collectors for Group Resolution Rules	Because IDCs no longer collect group data, you must edit the collector using the IDC and remove the IDC from the resolution list for groups. If you are reconfiguring ADCs to collect group data, replace the IDC with the ADC that collects the group data.
Cyclic Application Roles	<p>Cyclic application roles occur when an application role is collected as an entitlement member of itself, or when the application role is an entitlement in a child role. These cyclic relationships are no longer supported.</p> <p>To remove cyclic application roles:</p> <ol style="list-style-type: none"> 1. Edit the collector source data to remove cyclic relationships. 2. Run the collections to remove the cyclic relationships. 3. Rerun the migration report to verify that the cyclic application roles no longer exist.
Cyclic Global Roles	<p>Cyclic global roles occur when a role is collected as a member of itself. These cyclic relationships are no longer supported.</p> <p>To remove cyclic global roles:</p> <ol style="list-style-type: none"> 1. Edit the collector source data to remove cyclic relationships. 2. Run the collections to remove the cyclic relationships. 3. Rerun the migration report to verify that the cyclic roles no longer exist.
Cyclic Group Memberships	<p>Cyclic group memberships occur when a group is collected as a member of itself. These cyclic relationships are no longer supported.</p> <p>To remove cyclic group memberships:</p> <ol style="list-style-type: none"> 1. Edit the collector source data to remove cyclic relationships. 2. Run the collections to remove the cyclic relationships. 3. Rerun the migration report to verify that the cyclic groups no longer exist.
Duplicate Objects	<p>Duplicate objects occur when multiple collectors collect the same data for an application.</p> <p>To remove duplicate objects:</p> <ol style="list-style-type: none"> 1. Determine which data collector is incorrectly configured to collect duplicate objects. 2. Edit the data collector so that the query that it uses excludes the duplicate objects. <hr/> <p>Note: You may need to modify the source data to avoid collecting duplicates.</p> <hr/> <ol style="list-style-type: none"> 3. Save the changes to the collector. 4. Run the collector.

Report	Description and Issue Resolution Steps
	5. Verify the duplicate objects have been removed by running the migration report again.
EDCs Associated to RDCs	EDCs that are configured to process an RDC's entitlements.
EDCs Collecting Role Definitions	EDCs no longer collect data associated with roles. Role collectors collect all role definitions. You must reconfigure all EDCs after upgrading.
IDCs Configured to Collect Groups	IDCs no longer collect group data. If any IDCs collect groups, you must reconfigure them.
Roles Having Group Members	In previous versions, an RDC was associated with a single IDC. Values collected by the RDC were mapped to an attribute in the IDC, which restricted the collection of users to a particular IDC. In RSA Identity Governance and Lifecycle v7.0.1 and later, one or more target IDCs can be configured for the RDC, allowing resolution from multiple IDCs. Each target collector has a user attribute that resolves the collected user.

The Migration Report Utility

The Migration Report Utility identifies which data and collectors must be modified before the upgrade. The Migration Report Utility file (MigrationReports.zip) contains the following files used to identify installation issues.

File	Purpose
generateMigrationReport.sh	Creates a full migration report similar to a statistics report.
insertMigrationReportDefinitions.sh	Creates tabular report definitions for each report listed in the table in "Migration Reports."
insertMigrationReportDefinitions.sql	Used by the shell script for creating the tabular report definitions for the individual reports.
Pre_Migration_Pkg.pkb	Database package used by the full migration report.

See [Download the Migration Report Utility on page 12](#) for more information.

Download the Migration Report Utility

Download the Migration Report Utility (**MigrationReports.zip**) from RSA Link, extract the compressed file, and set the correct permissions on the reporting scripts.

Procedure

1. Download the **MigrationReports.zip** file from from RSA Link at <https://community.rsa.com/community/products/governance-and-lifecycle>.
2. Copy the zip file to the machine hosting the pre-7.0.2 RSA Identity Governance and Lifecycle database.
3. Log on to the database machine as root.

4. Extract the zip file to a temporary directory on the system. For example, on an RSA appliance extract to /tmp/aveksa.

5. Change the permissions on the script files to allow execution privileges. Enter

```
chmod 755 <filename>
```

where *<filename>* is the name of the script.

Install the Migration Reports

If you want to review individual reports for each type of issue that may affect your data, run the insertMigrationReportDefinitions.sh script to create the tabular report definitions for the individual migration reports.

If you are upgrading on WebSphere or WebLogic hosted on the AIX, see the Procedure (upgrading on WebLogic or WebSphere hosted on AIX) section below for instructions on how to install the migration reports on those platforms. You cannot run the insertMigrationReportDefinitions.sh bash shell script on AIX.

Procedure

1. Log on to the database machine as the oracle user.

Note: Ensure that the file for the script includes execution privileges.

2. Change to the directory containing the extracted Migration Utility scripts. For example, if you have extracted the scripts to /tmp/aveksa, enter

```
cd /tmp/aveksa/MigrationReports
```

3. At the command prompt, enter

```
insertMigrationReportDefinitions.sh
```

4. When prompted, enter the passwords for the AVUSER and the AVDWUSER.

After the script has created the reports, the following message displays:

```
Created required reports with Category Migration
```

Procedure (upgrading on WebLogic or WebSphere hosted on AIX)

Follow these instructions to install migration reports on WebLogic and WebSphere hosted on AIX.

1. cd to the database/Upgrade directory
2. Log on to sqlplus as avuser
3. Run the following commands:
 - a. whenever sqlerror exit 1 rollback

- b. whenever oserror exit 2 rollback

- c. set serveroutput on size 1000000

- d. @./insertMigrationReportDefinitions.sql;

- e. commit

4. Run the following transaction block:

```
BEGIN

FOR rec IN (select 'grant select on ' || TO_CHAR(view_name) || ' to
avdwuser' cmd

from avuser.T_AV_REPORTS

where regexp_like(view_name, '^[vV]_[a-zA-Z0-9_]+$')

and LENGTH(view_name) <= 30 AND REPORT_CATEGORY = 'Migration')

LOOP

EXECUTE IMMEDIATE rec.cmd;

END LOOP;

END;

/
```

5. commit;
6. Log out of sqlplus and log in again as avdwuser.
7. Run the following transaction block:

```
BEGIN

FOR rec IN (select 'create or replace synonym ' || TO_CHAR(view_name)
|| ' for avuser.' || TO_CHAR(view_name) cmd

from avuser.T_AV_REPORTS

where regexp_like(view_name, '^[vV]_[a-zA-Z0-9_]+$')

and LENGTH(view_name) <= 30 AND REPORT_CATEGORY = 'Migration')

LOOP

EXECUTE IMMEDIATE rec.cmd;

END LOOP;

END;

/

commit;
```

Run the Full Migration Report

The full migration report includes all migration issues and instructions for resolving them.

If you are upgrading on WebSphere or WebLogic hosted on the AIX, see the Procedure (upgrading on WebLogic

or WebSphere hosted on AIX) section below for instructions on running the migration reports on those platforms. You cannot run the generateMigrationReport.sh bash shell script on AIX.

Procedure

1. Log on to the database machine as the oracle user.

Note: Make sure that the file for the script includes execution privileges.

2. Go to the directory where you extracted MigrationReports.zip. For example:

```
cd /tmp/aveksa/MigrationReports
```

3. At the command prompt, enter

```
generateMigrationReport.sh
```

4. As prompted, provide the password for avuser.
5. View the full migration report in RSA Identity Governance and Lifecycle:
 - a. Log on to the RSA Identity Governance and Lifecycle.
 - b. Click Admin > System > Diagnostic.
 - c. Under Statistics Report in the row containing the report, do one of the following:
 - Download the report by clicking View.
 - Download a ZIP file containing the report by clicking Download.

Upgrade on WebLogic or WebSphere hosted on AIX

Follow these instructions to run the sqlplus command the generateMigrationReport.sh script ultimately calls.

Procedure

1. cd to the database/Upgrade directory.
2. Log on to sqlplus as avuser.
3. Run the following commands:
 - a. whenever sqlerror exit 1 rollback
 - b. whenever oserror exit 2 rollback
 - c. set serveroutput on size 1000000
 - d. @"./packages/Pre_Migration_Pkg.pkb";
 - e. exec Pre_Migration_Pkg.Save_Report;
 - f. commit

Run an Individual Migration Report

The individual migration reports list issues within a given category, for example, IDCs configured to collect user groups, and instructions for resolving the issue. For more information, see [Migration Reports on page 10](#).

Procedure

1. Log on to RSA Identity Governance and Lifecycle as an administrative.
2. Click Reports > Tabular.
3. In the Grouping drop-down list, select Type.
4. In the table of reports, click Migration (10).
5. Click the name of the report that you want to run.
6. Click Run Report.
7. Save the report results.
8. In the View Report screen do one of the following:
 - Export the results in a particular format:
 - a. Click Export.
 - b. Select the file type in which to save the report results.
 - c. Click OK.
 - Save the results for viewing in the RSA Identity Governance and Lifecycle console:
 - a. Click Save Results.
 - b. Enter a Description for the report results.
 - c. Click OK.

Note: RSA recommends that you perform these steps until the reports indicate no further issues, or until you have saved all of the necessary data.

Chapter 3: Pre-Upgrade Tasks for Migrating Group Business Descriptions

Read this chapter only if you are upgrading from the following versions of RSA Identity Governance and Lifecycle:

- RSA Identity Governance and Lifecycle 6.9.1 Patch 23 or earlier
- RSA Identity Governance and Lifecycle 7.0.1 Patch 3 or earlier
- RSA Identity Governance and Lifecycle 7.0.2 Patch 1 or earlier

When updating or migrating RSA Identity Governance and Lifecycle from a previous version, RSA Identity Governance and Lifecycle deletes group business descriptions that are not actively in use. Before you migrate, run the provided pre-migration queries to identify any group business descriptions that will be deleted by the migration process.

Review the results of each query to determine if any of the identified business descriptions are still needed. If you still need these group business descriptions, you can re-import them with an application reference in the import file, or you can manually recreate them after migration.

Unused Group Business Descriptions Not Associated with an Application

The following query identifies all group business descriptions that are not associated with an application, and that are currently unused. These business descriptions will be automatically deleted during migration.

```

SELECT
    id,
    'Group' as Type,
    object_filter AS "Object Filter",
    alt_name AS "Display Name",
    short_desc AS "Short Description",
    long_desc AS "Long Description",
    url_ref as "Help Link"
FROM
    t_av_business_description a
WHERE
    NOT EXISTS (
        SELECT

```

```

        application_id
    FROM
        t_groups b
    WHERE
        b.filter_id = a.id
    )
    AND a.scope_id IS NULL
    AND a.is_deleted = 'FALSE'
    AND a.object_type = 4
    AND a.applies_to_set = 'FALSE';

```

All Unused Group Business Descriptions

The following query identifies all unused group business descriptions regardless of their association with an application. These business descriptions will be automatically deleted during migration.

```

SELECT
    id,
    'Group' as Type,
    object_filter AS "Object Filter",
    alt_name AS "Display Name",
    short_desc AS "Short Description",
    long_desc AS "Long Description",
    url_ref as "Help Link",
    (select name from t_groups where id =
    a.scope_id) as "Group Name",
    (select name from t_applications where id =
    a.scope_id) as "Application Name"
FROM
    t_av_business_description a
WHERE
    NOT EXISTS (
        SELECT

```

```

        application_id
    FROM
        t_groups b
    WHERE
        b.filter_id = a.id
    )
    AND a.scope_id IS NOT NULL
    AND a.is_deleted = 'FALSE'
    AND a.object_type = 4
    AND a.applies_to_set = 'FALSE';

```

Group Business Description Table

As the ACM schema owner, run the following SQL statement to create a table that allows RSA Identity Governance and Lifecycle to determine a group's business description state during migration.

```

declare
v_tbl_count number;
Begin
    select count(*) into v_tbl_count
    from user_tab_columns
    where table_name = 'TEMP_BUSDESC';
    if v_tbl_count > 0 then
    execute immediate 'drop table temp_busdesc purge';
    end if;
    execute immediate
    'CREATE TABLE temp_busdesc
        AS
            SELECT
                name,
                id,
                filter_id,

```

```
        application_id
FROM
        t_groups
WHERE
        filter_id !=-1';

end;

/
```

Chapter 4: Verify Upgrade Prerequisites

Before you upgrade, verify that your current installation satisfies the prerequisites for your installation type:

- [Review Public Database Schema and Port Changes Introduced in v7.0.1](#)
- [Verify Prerequisites for an RSA Appliance](#)
- [Verify Prerequisites for a Software Bundle Installation](#)
- [Verify Prerequisites for Migration to a Virtual Application](#)
- [Verify Prerequisites for WebSphere](#)
- [Verify Prerequisites for Weblogic](#)
- [Additional Prerequisites for WebLogic and WebSphere Application Servers](#)

Review Public Database Schema and Port Changes Introduced in v7.0.1

Version 7.0.1 and later introduce changes to the public database schema. These changes may impact any report configurations that include queries against earlier product version public database schema views.

Database Schema Changes

Deprecated Collectors Table Columns:

- ROLE_COLLECTOR.USES_IDC_ID
- ENTITLEMENT_COLLECTOR.USES_RDC_ID
- MULTI_APP_COLLECTOR.USES_RDC_ID

New Entitlement Relationship Tables:

- ROLE_COLLECTOR.USES_IDC_ID
- ENTITLEMENT_COLLECTOR.USES_RDC_ID
- MULTI_APP_COLLECTOR.USES_RDC_ID
- BUSINESS_SOURCE
- DIRECT_UENTS_WITH_VIOLS
- UNIFIED_ENTITLEMENT

New Users Table:

USER_DATA_CLEANUP_ITEMS

Port Changes

Take note of the changes to the ports that use Secure Socket Layer (SSL).

Version	Changes
7.0.1 and later	Port 8443 connects through SSL. Port 8445 does not work.
6.9.1 and earlier	Port 8443 connects through SSL.

Version	Changes
	Port 8445 connects through non-SSL.

Verify Prerequisites for an RSA Appliance

Procedure

1. Verify that your appliance is supported for upgrade. RSA supports only RSA- or Aveksa-supplied hardware containing the following model numbers for upgrade.

Environment	Model Numbers
Development	Dell R320
Production	Dell R620 Dell R630 Dell R710 Dell R720 Dell R730

2. Verify that the appliance runs a supported version of RSA Identity Governance and Lifecycle, v6.9.1 or later. If the appliance runs an unsupported version and the hardware meets all other requirements, you must install a supported RSA Identity Governance and Lifecycle version before upgrading. For instructions, see the *Installation Guide* for the version you must install.
3. Verify that the appliance runs the following 64-bit operating system. See the *Installation Guide* for instructions for installing a new operating system if your operating system is out of date.

Operating System	Patch Level
SUSE Linux Enterprise Server 12	SP4 64-bit

4. Verify whether a valid Network Time Protocol (NTP) server is configured for RSA Identity Governance and Lifecycle. You may need to provide the IP address if the installation process cannot find the NTP server currently configured.
5. Verify that operating system /root volume has at least 16 GB of free disk space.

Verify Prerequisites for a Software Bundle Upgrade

Perform the following task to verify the prerequisites before performing a software bundle upgrade.

Procedure

1. Verify that the server where RSA Identity Governance and Lifecycle is installed meets the following requirements.

Component	Development Environment	Production Environment
RAM	48 GB with RSA-supplied database 16 GB with customer-supplied database	48 GB with RSA-supplied database 16 GB with customer-supplied database
Processor	Intel E5-2400 Quad Core	Dual Intel E5-2400 Quad Core
Disk Space	• 450 GB (RAID 1 or RAID 5)	• 1 TB + (RAID 1 or RAID 5)

Component	Development Environment	Production Environment
	<ul style="list-style-type: none"> 16 GB minimum for /root volume 	<ul style="list-style-type: none"> 16 GB minimum for /root volume
Network	Bond of NICs in active-backup bond mode	

- Verify that the installation server runs a supported version of RSA Identity Governance and Lifecycle, v6.9.1 or later. If the appliance runs an older, unsupported version and the hardware meets all other requirements, you must install a supported version before upgrading. For instructions, see the *Installation Guide* for the version you must install.
- Verify that the installation server runs one of the following 64-bit operating systems. If the server is not running a supported version of the operating system, you must upgrade the operating system and then perform a new installation of RSA Identity Governance and Lifecycle. For instructions on performing a new installation, see the *Installation Guide*.

Operating System	Patch Level
SUSE Linux Enterprise Server 12	SP2, SP3, or SP4; 64-bit
Red Hat Enterprise Linux 7	Minor version 2 or higher; 64-bit

Note: RSA Identity Governance and Lifecycle using the RSA-supplied database does not support automatic storage management (ASM).

- If you use a customer-supplied database, verify that is running Oracle 12.1.0.2. If it is not, upgrade to Oracle 12.1.0.2 before upgrading RSA Identity Governance and Lifecycle.

Note: When upgrading from 6.8.1 or 6.9.1, if your database is not already running Oracle 12.1.0.2, first back up the database, upgrade to Oracle 12.1.0.2, then restore and migrate the database. See [Back Up the Customer-Supplied Database](#) and [Import Your Customer-Supplied Database Backup and Migrate the Database](#) for instructions. See Oracle documentation for instructions on upgrading the database.

- Verify that required Oracle packages are installed on the same machine as the RSA Identity Governance and Lifecycle software.
 - See the "Package Requirements for Oracle Management Service" section at http://docs.oracle.com/cd/E29505_01/install.1111/e22624/preinstall_req_packages.htm
 - See the "Configuring Operating Systems for Oracle Grid Infrastructure and Oracle RAC" section at <http://docs.oracle.com/database/121/CWLIN/prelinux.htm#CWLIN168>
- Verify whether a valid Network Time Protocol (NTP) server is configured for RSA Identity Governance and Lifecycle. You may need to provide the IP address if the installation process cannot find the NTP server currently configured.

Verify Prerequisites for a Virtual Application

Verify that your environment meets the following requirements before upgrading or migrating to a virtual application:

- You can install the OVA using VMware ESXi version 5.x or higher.
- Virtual application deployments require a database deployed on a separate machine, which can either be a customer-supplied database or a database installed using the Database Installation Kit provided by RSA. The database must be installed on physical hardware, and not in a virtualized environment.

- The database is running Oracle 12.1.0.2. If it is not, upgrade to Oracle 12.1.0.2 before upgrading RSA Identity Governance and Lifecycle.
- A valid Network Time Protocol (NTP) server is configured for RSA Identity Governance and Lifecycle, to ensure that the time between the virtual application, database server, and any other connected systems are synchronized. You may need to provide the IP address if the installation process cannot find the NTP server currently configured.

Verify Prerequisites for WebSphere

The WebSphere application server where you install or upgrade RSA Identity Governance and Lifecycle must meet the following requirements.

Component	Requirement
RSA Identity Governance and Lifecycle Version	V6.9.1 or greater. If you are running an earlier, unsupported version, you must perform a new installation, which you can do as long as the system meets all of the other requirements listed in this table.
WebSphere Version	Either of the following: <ul style="list-style-type: none"> • IBM WebSphere Application Server Edition 8.5.5.x or 9.0 • IBM WebSphere Application Server Network Deployment Edition 8.5.5.x or 9.0
RAM	Production minimum requirement: 32 GB Note: You must allocate at least 8 GB of RAM to the RSA Identity Governance and Lifecycle server.
Operating System	An operating system that supports WebSphere
Database	An Oracle 12.1.0.2 instance configured to support RSA Identity Governance and Lifecycle. For more information about database requirements, see "Verify Prerequisites for a Customer-Supplied Database" in the <i>Installation Guide</i> . For instructions on configuring the customer-supplied database, see the <i>Database Setup and Management Guide</i> . If you are upgrading from or 6.9.1, do the following: back up the database, upgrade to Oracle 12.1.0.2, then restore and migrate the database. See Back Up the Customer-Supplied Database on page 30 and Import the Customer-Supplied Database Backup and Migrate the Database for instructions. See Oracle documentation for instructions on upgrading the database.
Disk Space	600 MB available for RSA Identity Governance and Lifecycle
Java	IBM JDK 1.7 (supported, but deprecated) or 1.8 (recommended)

Verify Prerequisites for WebLogic

The WebLogic application server where you install or upgrade RSA Identity Governance and Lifecycle must meet the following requirements.

Component	Requirement
RSA Identity Governance and Lifecycle Version	V6.9.1 or greater. If you are running an earlier, unsupported product version, you must perform a new installation, which you can do as long as the system meets all of the other requirements listed in this table.
WebLogic Version	12.1.x or 12.2.x
RAM	Production environment: 32 GB
	Note: You must allocate at least 8 GB of RAM to the RSA Identity Governance and Lifecycle server.
Operating System	An operating system that supports WebLogic
Database	An Oracle 12.1.0.2 instance configured to support RSA Identity Governance and Lifecycle. For more information about database requirements, see "Verify Prerequisites for a Customer-Supplied Database" in the <i>Installation Guide</i> . For information about configuring the customer-supplied database, see the <i>Database Setup and Management Guide</i> . If you are upgrading from 6.8.1 or 6.9.1, do the following: back up the database, upgrade to Oracle 12.1.0.2, then restore and migrate the database. See Back Up the Customer-Supplied Database on page 30 and Import the Customer-Supplied Database Backup and Migrate the Database for instructions. See Oracle documentation for instructions on upgrading the database.
Disk Space	600 MB available for RSA Identity Governance and Lifecycle
Java	Oracle JDK 1.7 (supported, but deprecated) or 1.8 (recommended)

Chapter 5: Prepare to Upgrade the RSA Identity Governance and Lifecycle Software

Before you upgrade, complete the preparation tasks for your upgrade scenario:

- [Back up the RSA Identity Governance and Lifecycle Application](#)
- [Apply the Latest Operating System and Database Patch Updates](#)
- [Back Up the RSA-Supplied Database](#)
- [Back Up the Customer-Supplied Database](#)
- [Prepare for an Upgrade on WebLogic](#)
- [Prepare for an Upgrade on WebSphere](#)

Ensure that your environment meets the prerequisites for your upgrade scenario as described in [Verify Upgrade Prerequisites](#) before you prepare for the upgrade.

Back up the RSA Identity Governance and Lifecycle Application

The following procedure applies only to appliance, software bundle, and virtual application deployments.

Back up RSA Identity Governance and Lifecycle configuration settings so they can be restored if needed. See "Restore RSA Identity Governance and Lifecycle" in the *Installation Guide* for information on restoring a software backup.

System metadata backed up from older versions is not supported in the latest release. A backup from an earlier version, if needed, must be restored in a fresh database that then must be upgraded.

If you are upgrading from a pre-7.0 version of RSA Identity Governance and Lifecycle, save any customization files from `/jboss-4.2.2.GA/server/default/deploy/aveksa.ear/aveksa.war` that you want to restore after the upgrade. As of version 7.0, customizations must be applied to the RSA Identity Governance and Lifecycle EAR file and then redeployed into the WildFly application server.

For information on restoring your customization files after the upgrade, see [Restore Your Customization Files](#).

RSA recommends that you store backups off of the system.

Procedure

1. Log in as the root user.
2. Stop AFX if it is installed:


```
<path-to-AFX>/afx stop
```
3. Change to the following directory path:


```
cd /home/oracle/deploy
```
4. Enter the following command:


```
./acm_backup.sh
```

5. Enter 'yes' to perform the backup operation.

The command creates a file named Backup<product version>.tar in the following directory:

```
/home/oracle/AveksaExportImportDir
```

Keep the Backup<product-version>.tar file in a safe place where it can be accessed in case you need to restore.

Apply the Latest Operating System and Database Patch Updates

RSA recommends that you download the Appliance Updater to apply the latest operating system (appliance only) and RSA-supplied database (appliance and software bundle installations) patches before you upgrade. The Updater bundles a certified patch set for the RSA-supplied operating system (SUSE) and the RSA-supplied Oracle database. Downloading and running the latest appliance updater closes vulnerabilities and addresses bugs.

On a quarterly basis, RSA bundles patches into a compressed file (rsaimg_updater_<release_date>_<platform>.tar.bz2) and posts it to RSA Link at <https://community.rsa.com/community/products/governance-and-lifecycle> for download.

For more information, see the *RSA Identity Governance and Lifecycle Appliance Updater Guide*, also available on RSA Link at <https://community.rsa.com/community/products/governance-and-lifecycle>.

Back Up the RSA-Supplied Database

Note: This task applies only to installations using an RSA-supplied Oracle database. If you use a customer-supplied database, see [Back Up the Customer-Supplied Database on page 30](#) for instructions.

This task creates a dump (.dmp) file of the AVUSER schema. The file contains all of the application data and some environment data about a particular system environment.

Procedure

1. Log in to the installation machine as the root user.
2. Enter the following command:

```
sudo service aveksa_server stop
```
3. Log on to the installation machine as the 'oracle' user.
4. Enter the following command:

```
(On a software bundle host): /home/oracle/database/DBA/AVDB/scripts/AVDB_Export_AVUSER.sh -t _Backup_Pre_Upgrade -o /home/oracle/upgradebackup
```

```
(On an appliance host): avdbexport -t _Backup_Pre_Upgrade -o /home/oracle/upgradebackup
```

The -t option, provides a tag name that is appended to the standard export file name. The script creates an export file named Export_AVDB_avuser_Backup_Pre_Upgrade.dmp file in the directory specified by the -o option. If -o option is not specified, the export file is saved to /home/oracle/AveksaExportImportDir/

Note: If you also want to compress the dump file, use the -g option.

Note: When using the -i option, ensure that the AVUSER and SYS database user passwords are the same. Both users are involved in executing the command. For more information on changing passwords, see "Changing Database User Passwords," in the *Installation Guide*.

5. Copy the .dmp file to an external location (off the appliance).
6. Check the results of the export process in the following log:

```
/home/oracle/AvekساExportImportDir/Export_AVDB_avuser_Backup_Pre_Upgrade.log
```

Back Up the Customer-Supplied Database

Before You Begin

- Ensure that the AVEKSA_EXPORTIMPORT_DIRECTORY directory has been created as described in "Set Up the Database" in the *Database Setup and Management Guide*
- Run the following query to identify if the directory structure exists, who owns it, and the directory that it points to on the database server:

```
select owner,directory_name, directory_path from all_directories
where directory_name = 'AVEKSA_EXPORTIMPORT_DIRECTORY';
```

- Run the following query to verify that the AVUSER or the schema owner has the appropriate privileges. The schema needs both Read and Write privileges.

```
select * from all_tab_privs
where table_name='AVEKSA_EXPORTIMPORT_DIRECTORY';
```

Procedure

1. Shut down the RSA Identity Governance and Lifecycle server before you export a database.
2. Shut down AFX if it is installed.
3. Run the following command from the database server machine:

```
expdp avuser/<password>@<Oracle_SID> DumpFile=<FileName>.dmp
Directory=Avekسا_ExportImport_Directory Schemas=avuser
LogFile=<FileName>.log
```

Where:

Expdp is the Oracle data pump utility.

avuser/<password> is the connection string.

DumpFile is the output file name; here set with a date stamp.

Directory is an internal Oracle directory object mapped to a physical UNIX directory. It would typically be the AvekساExportImportDir directory created when the customer-provided database was set up.

`Schemas` is the database, `avuser` for example.

`Logfile` is the name of the log file generated for the export.

Prepare for an Upgrade on WebLogic

Complete the following steps before you perform the upgrade.

Procedure

1. Make sure processing tasks are not running on the server:
 - a. Log in to RSA Identity Governance and Lifecycle.
 - b. Go to Admin > Monitoring to determine whether tasks are running.
 - c. Wait until all tasks have completed before proceeding with the upgrade.
2. Stop the RSA Identity Governance and Lifecycle server. See the Installation Guide for your current product version for instructions.
3. Stop AFX if it is installed.
4. Back up the database. For instructions, see [Back Up the Customer-Supplied Database on page 30](#).
5. Upgrade the database to Oracle 12.1.0.2.

Prepare for an Upgrade on WebSphere

Complete the following steps before you perform the upgrade.

Procedure

1. Make sure processing tasks are not running on the server:
 - a. Log in to RSA Identity Governance and Lifecycle.
 - b. Go to Admin > Monitoring to determine whether tasks are running.
 - c. Wait until all tasks have completed before proceeding with the upgrade.
2. Stop the RSA Identity Governance and Lifecycle server. See the Installation Guide for your current product version for instructions.
3. Stop AFX if it is installed.
4. Back up the database. See [Back Up the Customer-Supplied Database on page 30](#)
5. Upgrade the database to Oracle 12.1.0.2.

Chapter 6: Perform the Upgrade

The upgrade installs the latest version of RSA Identity Governance and Lifecycle. This chapter assumes that you performed all of the relevant prerequisite verifications and tasks in the previous chapters.

Note: The following procedures describe the process of upgrading to a new major, minor, or service pack release of RSA Identity Governance and Lifecycle. The procedures in this guide do not apply to installing a patch. For patch installation instructions, see the *RSA Identity Governance and Lifecycle Release Notes*.

See the section for your upgrade scenario:

- [Upgrade RSA Identity Governance and Lifecycle on an Appliance or Software Bundle Server](#)
- [Upgrade RSA Identity Governance and Lifecycle on WebSphere Application Server](#)
- [Upgrade RSA Identity Governance and Lifecycle on WebLogic Application Server](#)
- [Upgrade AFX](#)
- [Upgrade AFX If You Have a Pre-6.8.1 Version Installed](#)

If you plan to upgrade AFX along with RSA Identity Governance and Lifecycle, see [Upgrade AFX](#) for pre- and post-upgrade task instructions.

Upgrade RSA Identity Governance and Lifecycle on an Appliance or Software Bundle Server

To complete the upgrade, perform the following steps:

1. [Download the Installation Files](#)
2. [Copy the Downloaded Installation Files to the Installation Host](#)
3. [Run the Installation Script](#)
4. [Verify the Upgrade Succeeded \(RSA-Supplied Database\)](#)
5. [Verify Data Restoration and Start All Services](#)
6. [Confirm the Setting for the Encryption Key Directory](#)
7. [Re-install Remote Agents](#)
8. [Restore Your Customization Files](#)
9. [Delete the Jboss Folder \(When Upgrading From a Pre-v7.0 Product Version\)](#)
10. [Update Keystores on page 58](#)

Download the RSA Identity Governance and Lifecycle Installation Files

Procedure

1. Download the following installation files:
 - a. Go to [RSA Link](https://community.rsa.com/community/products/governance-and-lifecycle) (<https://community.rsa.com/community/products/governance-and-lifecycle>), then click Log In and enter your user name and password.
 - b. Click RSA Identity Governance and Lifecycle.
 - c. Click Downloads > RSA Identity Governance and Lifecycle 7.2.
 - d. Click Version Upgrades.

- e. Click the Upgrade link for your licensed RSA Identity Governance and Lifecycle asset.
- f. Click Continue.
- g. On the Order Detail page, click the menu icon and select Product List.

The Current tab lists the most recent release. The Archive tab lists previous releases.

- h. Click RSA Identity Governance and Lifecycle Version 7.2.
- i. Download the following files:
 - wildfly-10.1.0.Final.tar
 - adoptjdk_8u212b03.tar.gz
 - aveksa-<product-version>.tar.bz2
2. If you are using an RSA-supplied database, go back one screen, select Hardware Appliance Version 7.2, then download these files:
 - linuxamd64_12102_database_1of2.zip
 - linuxamd64_12102_database_2of2.zip
 - linuxamd64_12102_grid_1of2.zip
 - linuxamd64_12102_grid_2of2.zip
 - oracle_12.1.0.2_patches_v001.zip
 - asmlib-008_x64.tar.bz2
 - cvupack_Linux_x86_64.zip
 - redhat-release-6Server-1.noarch.rpm (Download only for a Software Bundle running Red Hat Enterprise Linux 6)
3. Download the appliance updater file for your installation:
 - rsaimg_updater_<release_date>_<platform>.tar.bz2.

Copy the Installation Files to the Installation Host

Procedure

1. Log in to the host as root or another user that is performing the installation.

Note: You are not required to use root, however non-root users are not able to update the sudoers file or create a system service to start and stop the application. The application does not require a system service to start and stop. The root user may be necessary to install the prerequisite JDK.

2. Create a directory for the packages. By default, this is /tmp/aveksa/packages. For example:

```
mkdir -p /tmp/aveksa/packages
```

Note: If the directory already exists, delete any files in the directory before you proceed.

3. Copy the downloaded installation package files to the directory.
4. Verify that the compressed package files you downloaded were not corrupted during the file transfer. Run the following commands in the /tmp/aveksa/packages directory:

- tar -jtvf on all downloaded .tar.bz2 files. For example:

```
tar -jtvf asmlib-008_x64.tar.bz2
```

- unzip -t on all downloaded .zip files. For example:

```
unzip -t linuxamd64_12102_database_1of2.zip
```

The commands list the packages and indicate if errors were detected.

5. If it already exists in your environment, delete the directory where the RSA Identity Governance and Lifecycle installation and product files are staged. For example:

```
/tmp/aveksa/staging
```

6. Expand the Aveksa package in a new staging directory. This can be any directory except in a hardware appliance, in which the /tmp/aveksa/staging directory is required. For example:

```
mkdir -p /home/aveksa/staging
```

```
cd /home/aveksa/staging
```

```
tar -jxvf /home/aveksa/packages/aveksa-  
<product-version>.tar.bz2
```

Run the Installation Script

Expect the upgrade procedure to consume 60 to 90 minutes.

The installation script performs checks for the following installation requirements:

- Memory
- Operating system packages
- Network settings
- User and group settings
- System configurations

The script displays information about the checks, and it indicates if a requirement is not met. After you resolve the requirement, you can run the script again.

Procedure

1. Log in to the installation host as root.
2. Run the upgrade script:

```
cd /tmp/aveksa/staging
```

```
./install.sh
```

Note: If the Access Fulfillment Express (AFX) module is installed on the RSA appliance where you are upgrading RSA Identity Governance and Lifecycle and you want to upgrade that AFX module, enter `install.sh -afx`. To upgrade AFX For all other RSA Identity Governance and Lifecycle deployment scenarios, you must perform the steps covered in [Upgrading AFX](#) or [Upgrade AFX If You Have a Pre-6.8.1 Version Installed](#).

3. Read and accept the license agreement.

A series of prompts and other information particular to your installation appears.

4. Enter "yes" at the following prompt:

```
Do you wish to install this version of RSA Identity Governance and
Lifecycle (yes or no)?
```

The installation begins. A summary displays information about the location of the installation and package files, and whether the Oracle database is a customer-supplied database. The default values on an RSA Identity Governance and Lifecycle appliance are:

```
Location of installation files: /tmp/aveksa/staging
```

```
Location of package files: /tmp/aveksa/packages
```

```
Use remote Oracle server: N
```

If you answered "Y" (Yes), the script displays the database connection information.

Note: If you created the database instance with non-default names for the database users, you must use the same usernames and passwords when prompted.

5. If the summary of install information is correct, enter "yes" at the following prompt:

```
Does this match your current install information (yes or no)?
```

If you enter "no," you are prompted to provide the correct information.

6. If you want to allow the installation to change the kernel settings, answer yes at the following prompt:

```
Do you want to run kernel settings change script now (yes or no)?
```

If you want to run the script yourself, answer no; the installation ends. You must then run the kernel settings change script (/tmp/modify_kernel_settings.sh), before running the installation script again.

7. If you backed up the database, enter BACKUP-OFFSITE-VERIFIED at the prompt. Otherwise, stop the installation, perform a backup, and run the installation script again.

8. If you are upgrading from v7.0.0 then enter Y at the following prompts:

```
An existing database was found. Do you want to keep the database
instance[Y]?
```

9. Log out all open sessions from the root account after the upgrade has finished.

To see what actions the installer performed during the upgrade, review the install log (/tmp/aveksa-install.log).

Verify the Upgrade Succeeded (RSA-Supplied Database)

Verify that the upgrade succeeded before you restore the database.

Procedure

1. Start all RSA Identity Governance and Lifecycle services:
 - a. Log in to the installation machine.
 - b. Start the RSA Identity Governance and Lifecycle server using the method appropriate for your deployment:

- If you have installed RSA Identity Governance and Lifecycle as the root user and installed it as a service, enter the following command:

```
sudo service aveksa_server start
```

- If you have installed RSA Identity Governance and Lifecycle as the AVEKSA_OWNER user, run the following from the deployment directory:

```
$AVEKSA_HOME/deploy/init.d/aveksa_server start
```

2. Log in to RSA Identity Governance and Lifecycle as AveksaAdmin (using the default password: aveksa123).

Note: If stored data must be re-encrypted because a key rollover was done, the Initialization Status indicates the startup process will re-encrypt the data. When the process is complete, you must restart RSA Identity Governance and Lifecycle.

3. To migrate the database, log in to RSA Identity Governance and Lifecycle. When you log in for the first time after upgrading, the Initialization Status indicates that the database schema is out-of-date. At the prompt, enter the following password: **AuthorizeMigration**. The start up process performs a migration of the database, which updates the schema.

Note: Before migrating the database, ensure that all product tables are uncompressed. If the tables are compressed, the migration process may perform operations that generate an Oracle error such as ORA-39726.

4. Restart the server after migration completes.
5. Log in to RSA Identity Governance and Lifecycle. Your upgrade has succeeded if you can successfully log in.

Verify Data Restoration and Start All Services

Perform this task to verify that data has been restored successfully and that you can start all services.

Procedure

1. Start all RSA Identity Governance and Lifecycle services:
 - a. Log in to the installation machine as the 'admin' user.
 - b. Enter the following command:

```
sudo service aveksa_server start
```

2. Log into RSA Identity Governance and Lifecycle as AveksaAdmin and verify that you have successfully imported your data.
3. If AFX is installed, start it.
4. Log out from RSA Identity Governance and Lifecycle.

Confirm the Setting for the Encryption Key Directory

The Key Encryption Key (KEK) is the key used to encrypt all other encryption keys. After installation (or upgrade), on first startup of RSA Identity Governance and Lifecycle, a unique KEK is created and stored in the encryption key directory. The default location of the directory is /home/oracle/security. If the default directory

is not available or you want to set a different directory, you must create the directory, and then specify the location in a Java system variable.

Procedure

1. Log in as root.

Note: You must log in as the root account to ensure that the proper permissions are granted. This procedure may not work using any other account.

2. Make sure you have a directory for storing the encryption key. For security purposes, the directory should have the following settings:
 - If the directory already exists, set its permissions to 700 (rwx-----) and make sure that the directory is owned by the same user under which RSA Identity Governance and Lifecycle is running.
 - If the directory does not exist, the parent directory must be writable for the user under which RSA Identity Governance and Lifecycle is running. In this case, RSA Identity Governance and Lifecycle will create the directory with the correct permissions.
 - For a cluster, this same directory also needs to exist on each of the nodes.
3. Confirm that the Java system property "rsavialg.security.keydir" is set to the appropriate directory. Use the steps for your platform in the following table to confirm or add the setting.

Platform:	Instructions:
Standalone	<p>The property is in aveksa-standalone-full.xml (/home/oracle/wildfly/standalone/configuration/aveksa-standalone-full.xml):</p> <pre><system-properties> <property name="rsavialg.security.keydir" value="/home/oracle/security"/> </system-properties></pre> <p>The default value for the directory is "/home/oracle/security" Change this to the directory where you will store the encryption key.</p>
Cluster	<p>On the Domain Controller, the property is in domain.xml (/home/oracle/wildfly/domain/configuration/domain.xml). Set the following values:</p> <pre><system-properties> <property name="rsavialg.security.keydir" value="/home/oracle/security"/> </system-properties></pre> <p>The default value for the directory is "/home/oracle/security" You should change this to the directory where you will store the encryption key</p> <p>The setting on the domain controller will be propagated to the other nodes in the cluster. Make sure you have the same encryption key directory on each of the nodes.</p>

4. Create a secure backup process to back up the keys in the encryption key directory. RSA Identity Governance and Lifecycle generates these keys and stores them only in the designated directory.

If the keys are lost, any data encrypted with those keys will be irrecoverable. The backup process should ensure that the keys are not compromised during the backup or after they are in the backup location.

Note: Anytime that you change the value of the Java system property after the keys have already been created (meaning after you configured the property and brought the system up), you must bring down the system and move the keys to the new location before bringing up the system again.

Using Non-restrictive Mode for the Encryption Key Directory

RSA recommends restricting access to the encryption key directory as stated in the previous section. If your installation cannot restrict the directory to the application owner and permissions as stated, you can implement a non-restrictive mode by using a Java system property named: `rsavialg.security.strict.permissions.disabled` .

When "`rsavialg.security.strict.permissions.disabled`" is set to be "true", restrictions on who owns the encryption key directory and what permissions are set on the directory are more flexible, but there are still requirements for permissions as described below.

Procedure

1. Add the "`rsavialg.security.strict.permissions.disabled`" property to system properties and set the value to "true" as shown for the platform type:

Platform:	Instructions:
Standalone	<p>The property is in <code>aveksa-standalone-full.xml</code> (<code>/home/oracle/wildfly/standalone/configuration/aveksa-standalone-full.xml</code>):</p> <pre><system-properties> <property name="rsavialg.security.keydir" value="/home/oracle/security"/> <property name="rsavialg.security.strict.permissions.disabled" value="true"/> </system-properties></pre>
Cluster	<p>On the Domain Controller, the property is in <code>domain.xml</code> (<code>/home/oracle/wildfly/domain/configuration/domain.xml</code>). Set the following values:</p> <pre><system-properties> <property name="rsavialg.security.keydir" value="/home/oracle/security"/> <property name="rsavialg.security.strict.permissions.disabled" value="true"/> </system-properties></pre>

2. Change the "`rsavialg.security.keydir`" property to the directory you want to use.
 - If the directory already exists, set its permissions such that the user (owner of the process under which RSA Identity Governance and Lifecycle is running) has "rwx" access into this directory. The owner of the directory need not be the same as the owner of the application process, but the owner of the application process must be able to read and write into this directory. This means "rwx" permissions have to be set for the appropriate file permission field (owner, group, all) , which will allow the application process full access.
 - If the directory does not exist, it is recommended that you create it. Set up the permissions on the directory as specified in the previous item.
 - If the directory does not exist and you do not create it, the application will attempt to create the directory on first startup using default permissions and the directory will be owned by the same user as the application process.

Note: Any time the value of the "`rsavialg.security.strict.permissions.disabled`" property is set or changed, the application server should be restarted.

Note: If "`rsavialg.security.strict.permissions.disabled`" is set to "false" or you remove this property, then standard "restrictive" handling for this directory will be used. If you had previously set up the directory for "non-restrictive" handling and switch to "restrictive" you must ensure this directory is set

up given the requirements outlined in "Confirm the Setting for the Encryption Key Directory" (see above).

Error Messages

The following table lists error messages that might display (in the AveksaServer.log) after you configure the encryption key directory. The table lists default directory paths for the master encryption key directory (/home/oracle/security) and its parent directory (/home/oracle). The suggested actions are performed on the RSA Identity Governance and Lifecycle host.

Message	Description	Action
KEK_ERROR_PARENT_DIRECTORY_DOES_NOT_EXIST	The parent directory /home/oracle for the specified encryption key storage directory /home/oracle/security does not exist.	Create the directory structure, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_PARENT_DIRECTORY_IS_NOT_WRITABLE	The parent directory /home/oracle for the specified encryption key storage directory /home/oracle/security is not writable.	Change permissions on the specified encryption key directory to allow RSA Identity Governance and Lifecycle to write to the directory.
KEK_ERROR_PARENT_IS_A_FILE	The parent /etc/hosts for the specified encryption key storage directory /etc/hosts/security is a file, not a directory.	Specify a directory path for the encryption key directory.
KEK_ERROR_FILE_ALREADY_EXISTS	A file already exists with the same path as the specified encryption key storage directory /etc/hosts.	Specify a directory location, not a file location.
KEK_ERROR_COULD_NOT_CREATE_DIRECTORY	Could not create the encryption key storage directory /home/oracle.	Create the directory, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_DIRECTORY_IS_NOT_WRITABLE	The encryption key storage directory /home/oracle is not writable.	Verify that directory permissions allow RSA Identity Governance and Lifecycle to write to the directory.
KEK_ERROR_DIRECTORY_DOES_NOT_EXIST	The encryption key storage directory /home/oracle does not exist.	Create the directory, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_INVALID_DIRECTORY_PERMISSIONS	The encryption key storage directory /home/oracle must have rwx----- (700) permissions. Please refer to the installation documentation for a system property that can be set to remove this restriction.	Verify that directory permissions allow RSA Identity Governance and Lifecycle to write to the directory. Alternatively, you can set a system property to remove this restriction. See "Using Non-restrictive Mode for the Encryption Key Directory" in the previous section.

Re-install Remote Agents

Remote agents are installed on systems from which you collect data, for example, your Microsoft Exchange server. After you upgrade your RSA Identity Governance and Lifecycle software, you must re-install any remote agents that you are using for collections. This allows the agents to use the updated cryptographic capabilities.

Before you begin

In RSA Identity Governance and Lifecycle, go to Collectors > Agents. If the agent is not running, then you must re-install.

Procedure

1. Connect to the host where the agent is installed, and then stop the agent:
 - On Linux: `service aveksa_agent stop`
 - On Windows, use the Windows Services Control Panel applet to stop the service.
2. Back up the previous version of the agent. Connect to the host where the agent is installed and copy the files to another location.

Note: The default agent, AveksaAgent, is installed in the AveksaAgent directory on the remote system.

3. Remove the agent by deleting the files from the agent directory.
4. Get the updated agent files by downloading the new archive file from the agent detail page.
 - a. Log on to the appliance where RSA Identity Governance and Lifecycle is installed, click Collectors > Agents, then select an agent.
 - b. Click Download Agent.
5. Copy the agent archive file from the download directory. Connect to the agent host and copy the archive file to the agent directory.
6. Unzip the agent file, AveksaAgent.zip for example.
7. Start the agent service as follows:
 - On Linux: `service aveksa_agent start`
 - On Windows, use the Windows Services Control Panel applet to start the service.
8. To verify that RSA Identity Governance and Lifecycle can connect to the agent, click Collectors > Agents. The status for "Is Running" should be Yes.

Restore Your Customization Files

This section describes how to restore your customization files after the upgrade that you may have saved from the your pre-7.0 version of RSA Identity Governance and Lifecycle. Customizations must be applied to the RSA Identity Governance and Lifecycle application EAR file and redeployed into the WildFly application server.

Procedure

1. Log on to your installation appliance or server as the oracle user.
2. Go to the following directory:

```
cd /home/oracle/deploy
```

3. Enter the following command:


```
customizeACM.sh -c
```

4. Answer "Yes" to expand the EAR.
5. Upload the customization files you saved before the upgrade to the following directory:

```
/tmp/customizeACM
```

6. Go to the following directory:

```
cd /home/oracle/deploy
```

7. Repack the EAR with your customization files by running the following command:

```
customizeACM.sh -d
```

Delete the Jboss Folder (When Upgrading From a Pre-v7.0 Product Version)

This task is required when you are upgrading from a pre-V7.0 version of RSA Identity Governance and Lifecycle. With the the WildFly application server, you do not require the Jboss folder or its contents from the previous product version.

Procedure

1. Log on to the installation machine as root user.
2. Change to `/home/oracle`.
3. Delete the jboss folder. Enter

```
rm -rf jboss
```

Upgrade RSA Identity Governance and Lifecycle on WebSphere Application Server

To complete the upgrade, perform the following steps:

1. [Update the ACM Oracle JDBC Provider](#) (for upgrading from 7.0.1 and earlier)
2. [Update the AVDWDB Data Source in WebSphere on page 42](#)
3. [Deploy the WebSphere Installation EAR Files](#)
4. [Configure the RSA Identity Governance and Lifecycle Shared Library on page 44](#)
5. [Update the Setting for the Encryption Key Directory](#)

Before you begin

In a clustered environment, consider the following:

- The deployment process requires a single connection to the database for setup and migration. Therefore, a single node only must be used during the process. Ensure that only one server instance is running and connected to the database instance. Shut down AFX if it is installed.
- After node is updated, verify that you can start RSA Identity Governance and Lifecycle and start the other nodes. For instructions managing RSA Identity Governance and Lifecycle instance nodes in the cluster, see the Help topic, "Manage Server Cluster Nodes."

After you finish

Re-install the remote agents. For instructions, see [Re-install Remote Agents](#).

Note: After the upgrade, the data sources WPDS, WPDS2, and WPDS3 are no longer used and can be safely removed.

Update the ACM Oracle JDBC Provider

A JDBC provider enables RSA Identity Governance and Lifecycle to access data sources. Use the JDBC drivers provided in the ACM-WebSphere.tar file.

Procedure

1. In the WebSphere console, from the Resources menu, select JDBC > JDBC Providers.
2. Set the scope:
 - (Standalone) Node= <machine-name>Node01, server=server1)
 - (Cluster) cluster=MyCluster
3. Click ACM Oracle JDBC Driver to update the JDBC Provider:
 - Database type: Oracle
 - Provider type: Oracle JDBC Driver
 - Implementation type: Connection pool data source
 - Name: ACM Oracle JDBC Driver
4. Click Update to enter database classpath information with the newer JDBC jar files.
5. In the Class Path section, update the following three lines, separated by the ENTER key:


```

${ORACLE_JDBC_DRIVER_PATH}/ojdbc8.jar

${ORACLE_JDBC_DRIVER_PATH}/xdb6.jar

${ORACLE_JDBC_DRIVER_PATH}/xmlparserv2_sans_jaxp_services.jar

```
6. In the Directory location for ojdbc8.jar section, enter the location of the following JDBC jar files: ojdbc8.jar, xdb6.jar, xmlparserv2_sans_jaxp_services.jar.
7. Save changes to the master configuration.
8. (Clusters only) Restart the server and node agents after configuration of the JDBC Provider and before the creation of the JDBC data sources.

Update the AVDWDB Data Source in WebSphere

In a WebSphere environment, you must perform the following procedure to manually update the AVDWDB data source.

Procedure

1. In the WebSphere administrative console, go to **Resources > JDBC > Data sources**.
2. Select the AVDWDB data source, and open the WebSphere Application Server data source properties.
3. Select **Non-transactional data source**.
4. Restart the application server.

Deploy the WebSphere Installation EAR Files

This section describes how to upgrade the Aveksa EAR and deploy the aveksaWFArchitect.ear file for the

Workflow Architect. The Workflow Architect is used in RSA Identity Governance and Lifecycle to view and edit workflows.

Procedure

1. Download the following upgrade file to the WebSphere host:
 - a. Go to [RSA Link](https://community.rsa.com/community/products/governance-and-lifecycle) (https://community.rsa.com/community/products/governance-and-lifecycle), then click Log In and enter your user name and password.
 - b. Click RSA Identity Governance and Lifecycle.
 - c. Click Downloads > RSA Identity Governance and Lifecycle 7.2.
 - d. Click on Additional Downloads.
 - e. Click Access Certification Manager.
 - f. Click Download Software (it may take a minute to display the Product List).
 - g. Click RSA Identity Governance and Lifecycle (formerly Aveksa) - Version Upgrades.

The Current tab lists the most recent release. The Archive tab lists previous releases.
 - h. Click Access Certification Manager Version 7.2.
 - i. Download the following files:
 - ACM-WebSphere-<product version>.tar
2. Untar the file. Enter


```
tar xvf ACM-WebSphere <product version>.tar
```

This creates a directory named ACM-WebSphere-<version> that contains the EAR files for deployment.
3. Apply any customization changes to the EAR files if required. See "Modifying the RSA Identity Governance and Lifecycle Enterprise Archive" in the *Installation Guide* for more information.
4. Upgrade the Aveksa EAR.
 - a. From the Applications menu, click Application Types > WebSphere Enterprise Applications
 - b. Select the application and click the Upgrade button to upload the updated EAR or WAR.
 - c. Select Replace the entire application and select the path to the replacement ACM EAR file to upload and specify the context, 'aveksa.' Continue through the wizard (choose Fast Path). For full instructions, see the *RSA Identity Governance and Lifecycle Installation Guide*.
 - d. Finish installing the EAR, which may take several minutes.
 - e. Save changes to the master configuration.
5. Deploy the Workflow Architect EAR.
 - a. From Applications menu, click Application Types > WebSphere Enterprise Applications, and then click Install, or Upgrade if upgrading an existing EAR. Continue through the wizard (choose Fast Path).
 - b. Browse to the aveksaWFArchitect.ear file in the ACM-WebSphere-<version>. The installation process continues through several pages. Accept default values where not indicated otherwise.
 - c. (Clustered environment only) Select Map Modules to Servers: Select all the modules, select the correct scope from the list of Clusters and Servers, and then click Apply. The server associated with the module should be listed as the cluster. Click Next.
 - d. In the Map Virtual Hosts for Web Modules screen, click Next.
 - e. Finish installing the EAR, which may take several minutes.

- f. Save changes to the master configuration.
6. Restart the WebSphere application server.
7. Start the RSA Identity Governance and Lifecycle application on the single designated deployment node only in a clustered environment.
8. Log on to RSA Identity Governance and Lifecycle to verify a successful upgrade.
9. If you see the Initialization Status prompt, one or both of these cases apply:
 - The database schema is out-of-date. At the prompt, enter the password: AuthorizeMigration. The startup process migrates the database, which updates the schema.
 - Stored data needs to be re-encrypted because a key rollover was done. The startup process re-encrypts the data.

Note: If the Initialization Status displays an "Unable to check Database" error, you must restart the WebSphere server.

10. Restart the RSA Identity Governance and Lifecycle application, and also restart AFX if it is installed.

Note: If the installation fails, RSA recommends that you first uninstall RSA Identity Governance and Lifecycle, restart your application server and reinstall RSA Identity Governance and Lifecycle.

Configure the RSA Identity Governance and Lifecycle Shared Library

This step is required as part of the WebSphere upgrade process.

Before you begin

Deploy the Aveksa EAR. See [Deploy the WebSphere Installation EAR Files on page 42](#).

To configure the shared library:

1. From the WebSphere admin console, go to Environment > Shared libraries.
2. Set the scope for your configuration:
 - (Standalone) Node=<machine-name>Node01, server=server1
 - (Cluster) cells=MyCluster
3. Click New to create the shared library:
 - Name: Aveksa Shared Library
 - Classpath: Full path to hibernate-jpa-2.0-api-1.0.1.Final.jar and javassist-3.18.1-GA.jar that is included in the DISTRIBUTION directory. For example, if your DISTRIBUTION directory is /opt/ACM-WebSphere-<product version> then the full path would be /opt/ACM-WebSphere-<product version>/hibernate-jpa-2.0-api-1.0.1.Final.jar and /opt/ACM-WebSphere-<product version>/javassist-3.18.1-GA.jar
4. Under the Class Loading section, select Use an isolated class loader for this shared library.

To associate the Aveksa Shared Library with the Aveksa EAR:

1. From the WebSphere admin console, go to Applications > Application Types > WebSphere enterprise applications.
2. Select the aveksa application on the Enterprise Applications page.
3. Under the References section, click the Shared library references link.
4. Select the aveksa application, and then click Reference shared libraries.

5. On the Shared Library Mapping page, select Aveksa Shared Library from the Available list and move it to the Selected list.
6. Click OK to save changes.

Update the Setting for the Encryption Key Directory

The Key Encryption Key (KEK), is the key used to encrypt all other encryption keys. The upgrade creates a unique KEK and stores it in the encryption key directory. The default location of the directory is `/home/oracle/security`. If the default directory is not available or you want to set a different directory, you must create the directory, and then specify the location in a Java system variable.

Procedure

1. Log in to the WebSphere host as administrator with root privileges.
2. Make sure you have a directory for storing the key encryption key. For security purposes, the directory should have the following settings::
 - If the directory already exists, set write permissions to 700 (rwx-----) for the user under which RSA Identity Governance and Lifecycle is running.
 - If the directory does not exist, the parent directory must be writable for the user under which RSA Identity Governance and Lifecycle is running. In this case, RSA Identity Governance and Lifecycle will create the directory with the correct permissions.
3. Set the Java system property "rsavialg.security.keydir" to the directory where the encryption key is stored. Perform these steps in the Admin console for WebSphere:
 1. To select the server, click Servers > Server types > WebSphere application servers > Select server.
 2. Choose the server used for RSA Identity Governance and Lifecycle.
 3. Under the Configuration tab, select Server Infrastructure > Java and Process Management > Process Definition.
 4. Under Additional Properties, select Java Virtual Machine > Custom Properties.
 5. Select New, then enter:

Name: rsavialg.security.keydir

Value: <directory path for master encryption key>

For example, in a standalone environment:

```
rsavialg.security.keydir=<directory path for the encryption key>
```

For example, in a cluster environment:

```
rsavialg.security.keydir=<server and directory path for the master encryption key>,
where server is the hostname of a common network path that is accessible from all nodes. (You
could also set this up on each node by defining a local directory path on each node.)
```

4. Create a secure backup process to back up the keys that are in the encryption key directory. RSA Identity Governance and Lifecycle generates these keys and stores them only in the designated directory.

If the keys are lost, any data encrypted with those keys will be irrecoverable. The backup process should ensure that the keys are not compromised, or otherwise exposed, during the backup or after they are in the backup location.

Note: Anytime that you change the value of the Java system property after the keys have already been created

(meaning after you configured the property and brought the system up), you must bring down the system and move the keys to the new location before bringing up the system again.

Using Non-restrictive Mode for the Encryption Key Directory

RSA recommends restricting access to the encryption key directory as stated in the previous section. If your installation cannot restrict the directory to the application owner and permissions as stated, you can implement a non-restrictive mode by using a Java system property named: `rsavialg.security.strict.permissions.disabled` .

When "`rsavialg.security.strict.permissions.disabled`" is set to be "true", restrictions on who owns the encryption key directory and what permissions are set on the directory are more flexible, but there are still requirements for permissions as described below.

Procedure

1. In the Admin console, add a java system property named "`rsavialg.security.strict.permissions.disabled`" property and set the value to "true" as shown for the platform type:
 1. To select the server, click Servers > Server types > WebSphere application servers > Select server.
 2. Choose the server used for RSA Identity Governance and Lifecycle.
 3. Under the Configuration tab, select Server Infrastructure > Java and Process Management > Process Definition.
 4. Under Additional Properties, select Java Virtual Machine > Custom Properties.
 5. Select New, then enter:

Name: `rsavialg.security.strict.permissions.disabled`

Value: true

2. Change the "`rsavialg.security.keydir`" property to the directory you want to use.

If the directory already exists, set its permissions such that the user (owner of the process under which RSA Identity Governance and Lifecycle is running) has "rwx" access into this directory. The owner of the directory need not be the same as the owner of the application process, but the owner of the application process must be able to read and write into this directory. This means "rwx" permissions have to be set for the appropriate file permission field (owner, group, all) , which will allow the application process full access.

If the directory does not exist, it is recommended that you create it. Set up the permissions on the directory as specified in the previous item.

If the directory does not exist and you do not create it, the application will attempt to create the directory on first startup using default permissions and the directory will be owned by the same user as the application process.

Note: Any time the value of the "`rsavialg.security.strict.permissions.disabled`" property is set or changed, the application server should be restarted.

Note: If "`rsavialg.security.strict.permissions.disabled`" is set to "false" or you remove this property, then standard "restrictive" handling for this directory will be used. If you had previously set up the directory for "non-restrictive" handling and switch to "restrictive" you must ensure this directory is set up given the requirements outlined in "Confirm the Setting for the Encryption Key Directory" (see above).

Error Messages

The following table lists error messages that might display after you configure the encryption key directory. The table lists default directory paths for the encryption key directory (/home/oracle/security) and its parent directory (/home/oracle). The suggested actions are performed on the RSA Identity Governance and Lifecycle host.

Message	Description	Action
KEK_ERROR_PARENT_DIRECTORY_DOES_NOT_EXIST	The parent directory /home/oracle for the specified encryption key directory /home/oracle/security does not exist.	Create the directory structure, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_PARENT_DIRECTORY_IS_NOT_WRITABLE	The parent directory /home/oracle for the specified encryption key directory /home/oracle/security is not writable.	Change permissions on the specified encryption key directory to allow RSA Identity Governance and Lifecycle to write to the directory.
KEK_ERROR_PARENT_IS_A_FILE	The parent /etc/hosts for the specified encryption key directory /etc/hosts/security is a file, not a directory.	Specify a directory path for the encryption key directory.
KEK_ERROR_FILE_ALREADY_EXISTS	A file already exists with the same path as the specified encryption key directory /etc/hosts.	Specify a directory location, not a file location.
KEK_ERROR_COULD_NOT_CREATE_DIRECTORY	Could not create the encryption key directory /home/oracle.	Create the directory, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_DIRECTORY_IS_NOT_WRITABLE	The encryption key directory /home/oracle is not writable.	Verify that directory permissions allow RSA Identity Governance and Lifecycle to write to the directory.
KEK_ERROR_DIRECTORY_DOES_NOT_EXIST	The encryption key directory /home/oracle does not exist.	Create the directory, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_INVALID_	The encryption key directory /home/oracle must have rwx--- (700) permissions. Please refer to the installation	Verify that directory permissions allow RSA

Message	Description	Action
DIRECTORY_ PERMISSIONS	documentation for a system property that can be set to remove this restriction.	Identity Governance and Lifecycle to write to the directory. Alternatively, you can set a system property to remove this restriction. See "Using Non-restrictive Mode for the Encryption Key Directory" in the previous section.

Upgrade RSA Identity Governance and Lifecycle on WebLogic Application Server

To complete the upgrade, perform the following steps:

1. [Update the AVDWDB Data Source in WebLogic on page 48](#)
2. [Deploy the WebLogic Installation EAR Files](#)
3. [Update the Setting for the Encryption Key Directory](#)

Before you begin

In a clustered environment, consider the following:

- The deployment process requires a single connection to the database for setup and migration. Therefore, a single node only must be used during the process. Ensure that only one server instance is running and connected to the database instance. Shut down AFX if it is installed.
- After node is updated, verify that you can start RSA Identity Governance and Lifecycle and start the other nodes. For instructions managing RSA Identity Governance and Lifecycle instance nodes in the cluster, see the Help topic, "Manage Server Cluster Nodes."

After you finish

Re-install the remote agents. For instructions, see [Re-install Remote Agents](#).

Note: After the upgrade, the data sources WPDS, WPDS2, and WPDS3 are no longer used and can be safely removed.

Update the AVDWDB Data Source in WebLogic

In a WebLogic environment, you must perform the following procedure to manually update the AVDWDB data source.

Procedure

1. In the WebLogic administrative console, go to **Services > Data sources**.
2. Select the AVDWDB data source, and open the Transaction tab.
3. Make sure that **Supports Global Transactions** is not selected.
4. Under Data Sources, select the AVDB data source, and open the Transaction tab.

5. Select **Logging Last Resource**.
6. Restart the application server.

Deploy the WebLogic Installation EAR Files

This section describes how to upgrade the Aveksa EAR and deploy the aveksaWFArchitect.ear file for the Workflow Architect. The Workflow Architect is used in RSA Identity Governance and Lifecycle to view and edit workflows.

Procedure

1. Download the following upgrade file to the WebLogic host:
 - a. Go to [RSA Link](https://community.rsa.com/community/products/governance-and-lifecycle) (https://community.rsa.com/community/products/governance-and-lifecycle), then click Log In and enter your user name and password.
 - b. Click RSA Identity Governance and Lifecycle.
 - c. Click Downloads > RSA Identity Governance and Lifecycle 7.2.
 - d. Click on Additional Downloads.
 - e. Click Access Certification Manager.
 - f. Click Download Software (it may take a minute to display the Product List).
 - g. Click RSA Identity Governance and Lifecycle (formerly Aveksa) - Version Upgrades.

The Current tab lists the most recent release. The Archive tab lists previous releases.

- h. Click Access Certification Manager Version 7.2.
 - i. Download the following files:
 - ACM-WebLogic-<product version>.tar

2. Untar the file. Enter

```
tar xvf ACM-WebLogic <product version>.tar
```

This creates a directory named ACM-WebLogic-<version> that contains the EAR files for deployment.

3. Apply any customization changes to the upgrade EAR files if required. For more information, see "Modifying the RSA Identity Governance and Lifecycle Enterprise Archive" in the *Installation Guide.7.2*
4. Upgrade the Aveksa EAR :
 - a. From the WebLogic Administrative Console, click Deployments > aveksa > Delete.
 - b. Click Deployments > Install.
 - c. Browse to aveksa.ear. For example: ACM-WebLogic_<version>/aveksa.ear. The path might be different for a customized aveksa.ear.
 - d. Choose Install this deployment as an application.
 - e. Set Name to aveksa.
 - f. Choose Copy this application to every target for me under Source accessibility. Continue to the next page.
 - g. Under Additional configuration choose: No, I will review the configuration later.

5. Deploy the Workflow Architect ear:
 - a. Select Deployments > Install.
 - b. Browse to aveksaWFArchitect.ear. For example: ACM-WebLogic /aveksaWFArchitect.ear. The path may differ for a patch.
 - c. Install this deployment as an application.
 - d. Select deployment targets: the server for a standalone server environment or the cluster for a clustered environment.
 - e. Choose Copy this application to "every target for me" under Source accessibility.
 - f. In Additional configuration choose: No, I will review the configuration later.
 - g. Click Finish.
6. Restart the WebLogic application server.
7. Start the RSA Identity Governance and Lifecycle application on the single designated deployment node only in a clustered environment.
8. Log on to RSA Identity Governance and Lifecycle to verify a successful upgrade..
9. If you see the Initialization Status prompt when you start RSA Identity Governance and Lifecycle, one or both of these cases apply:
 - The database schema is out-of-date. At the prompt, enter the following password: "AuthorizeMigration." The startup process migrates the database, which updates the schema.
 - Stored data needs to be re-encrypted because a key rollover was done. The startup process re-encrypts the data.

Note: If the Initialization Status displays an "Unable to check Database" error, you must restart the WebLogic server.

10. Restart the RSA Identity Governance and Lifecycle application.

Note: If the installation fails, RSA recommends that you first uninstall RSA Identity Governance and Lifecycle, restart your application server and reinstall RSA Identity Governance and Lifecycle.

Update the Setting for the Encryption Key Directory

The Key Encryption Key (KEK) is the key used to encrypt all other encryption keys. The upgrade creates a unique KEK and stores it in the encryption key directory. The default location of the directory is /home/oracle/security. If the default directory is not available or you want to set a different directory, you must create the directory manually, and then specify the location using a Java system variable.

Procedure

1. Log in to the WebLogic host as administrator with root privileges.
2. Make sure you have a directory for storing the key encryption key. For security purposes, the directory should have the following settings:
 - If the directory already exists, set its permissions to 700 (rwx-----) and make sure that the directory is owned by the same user under which RSA Identity Governance and Lifecycle is running.
 - If the directory does not exist, the parent directory must be writable for the user under which RSA Identity Governance and Lifecycle is running. In this case, RSA Identity Governance and Lifecycle will create the directory with the correct permissions.

3. Set the Java system property "rsavialg.security.keydir" to the directory where the encryption key is stored.
4. There are two ways to set JVM arguments in WebLogic installations. These methods might not map to your environment if you use custom scripts for starting a WebLogic application server instance. See your WebLogic administrator to configure the JVM setting for your environment.

- Edit the WebLogic Domain startup environment script. This is typically done on a standalone system and is required if using the AdminServer as the instance where you are deploying RSA Identity Governance and Lifecycle.

Edit the setDomainEnv.sh file for the domain in which you will be deploying the RSA Identity Governance and Lifecycle application.

For example, from \$WEBLOGIC_HOME/user_projects/domains/<domain_name>/bin, add the following settings to the beginning of the setDomainEnv script, where WL_HOME is set.

```
JAVA_OPTIONS="$JAVA_OPTIONS -Drsavialg.security.keydir=<directory path for the encryption key>"
```

```
export JAVA_OPTIONS
```

For example, in a standalone environment:

```
JAVA_OPTIONS="$JAVA_OPTIONS
-Drsavialg.security.keydir="/wls/masterkeystorage"
```

For example, in a cluster environment:

```
JAVA_OPTIONS="$JAVA_OPTIONS -Drsavialg.security.keydir="/wls/masterkeystorage"
```

- Use the Administration Console to specify JVM arguments for a server instance. This is typically used if your servers are managed through NodeManager.

From the Administration Console:

1. Click Environment > Servers > Select server.
2. Click Configuration tab > Server Start tab.
3. Add the startup setting -Drsavialg.security.keydir=<directory path for the encryption key> to the Arguments field .

Using Non-restrictive Mode for the Encryption Key Directory

RSA recommends restricting access to the encryption key directory as stated in the previous section. If your installation cannot restrict the directory to the application owner and permissions as stated, you can implement a non-restrictive mode by using a Java system property named: rsavialg.security.strict.permissions.disabled .

When "rsavialg.security.strict.permissions.disabled" is set to be "true", restrictions on who owns the encryption key directory and what permissions are set on the directory are more flexible, but there are still requirements for permissions as described below.

Procedure

1. Add a java system property named "rsavialg.security.strict.permissions.disabled" property and set the value to "true" as shown for the platform type:

There are two ways to set JVM arguments in WebLogic installations. These methods might not map to

your environment if you use custom scripts for starting a WebLogic application server instance. See your WebLogic administrator to configure the JVM setting for your environment.

- Edit the WebLogic Domain startup environment script. This is typically done on a standalone system and is required if using the AdminServer as the instance where you are deploying RSA Identity Governance and Lifecycle.

Edit the `setDomainEnv.sh` file for the domain in which you will be deploying the RSA Identity Governance and Lifecycle application.

For example, from `$WEBLOGIC_HOME/user_projects/domains/<domain_name>/bin`, add the following settings to the beginning of the `setDomainEnv` script, where `WL_HOME` is set.

```
JAVA_OPTIONS="$JAVA_OPTIONS -Drsavialg.security.strict.permissions.disabled=true"
export JAVA_OPTIONS
```

For example, in a standalone environment:

```
JAVA_OPTIONS="$JAVA_OPTIONS
-Drsavialg.security.strict.permissions.disabled=true"
```

For example, in a cluster environment:

```
JAVA_OPTIONS="$JAVA_OPTIONS -Drsavialg.security.strict.permissions.disabled=true"
```

- Use the Administration Console to specify JVM arguments for a server instance. This is typically used if your servers are managed through NodeManager.

From the Administration Console:

1. Click Environment > Servers > Select server.
2. Click Configuration tab > Server Start tab.
3. Add the startup setting `-Drsavialg.security.strict.permissions.disabled=true` to the Arguments field .

2. Change the `"rsavialg.security.keydir"` property to the directory you want to use.

If the directory already exists, set its permissions such that the user (owner of the process under which RSA Identity Governance and Lifecycle is running) has "rwx" access into this directory. The owner of the directory need not be the same as the owner of the application process, but the owner of the application process must be able to read and write into this directory. This means "rwx" permissions have to be set for the appropriate file permission field (owner, group, all) , which will allow the application process full access.

If the directory does not exist, it is recommended that you create it. Set up the permissions on the directory as specified in the previous item.

If the directory does not exist and you do not create it, the application will attempt to create the directory on first startup using default permissions and the directory will be owned by the same user as the application process.

Note: Any time the value of the `"rsavialg.security.strict.permissions.disabled"` property is set or changed, the application server should be restarted.

Note: If `"rsavialg.security.strict.permissions.disabled"` is set to "false" or you remove this property, then standard "restrictive" handling for this directory will be used. If you had previously set up the

directory for “non-restrictive” handling and switch to “restrictive” you must ensure this directory is set up given the requirements outlined in “Confirm the Setting for the Encryption Key Directory” (see above).

Error Messages

The following table lists the error messages that might display after you configure the encryption key directory. The table lists default directory paths for the encryption key directory (/home/oracle/security) and its parent directory (/home/oracle). The suggested actions are performed on the RSA Identity Governance and Lifecycle host.

Message	Description	Action
KEK_ERROR_PARENT_DIRECTORY_DOES_NOT_EXIST	The parent directory /home/oracle for the specified encryption key directory /home/oracle/security does not exist.	Create the directory structure, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_PARENT_DIRECTORY_IS_NOT_WRITABLE	The parent directory /home/oracle for the specified encryption key directory /home/oracle/security is not writable.	Change permissions on the specified encryption key directory to allow RSA Identity Governance and Lifecycle to write to the directory.
KEK_ERROR_PARENT_IS_A_FILE	The parent /etc/hosts for the specified encryption key directory /etc/hosts/security is a file, not a directory.	Specify a directory path for the encryption key directory.
KEK_ERROR_FILE_ALREADY_EXISTS	A file already exists with the same path as the specified encryption key directory /etc/hosts.	Specify a directory location, not a file location.
KEK_ERROR_COULD_NOT_CREATE_DIRECTORY	Could not create the encryption key directory /home/oracle.	Create the directory, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_DIRECTORY_IS_NOT_WRITABLE	The encryption key directory /home/oracle is not writable.	Verify that directory permissions allow RSA Identity Governance and Lifecycle to write to the directory.
KEK_ERROR_DIRECTORY_DOES_NOT_EXIST	The encryption key directory /home/oracle does not exist.	Create the directory, set permissions to allow RSA Identity Governance and Lifecycle to read from and write to the directory, and specify the encryption key directory again.
KEK_ERROR_INVALID_DIRECTORY_PERMISSIONS	The encryption key directory /home/oracle must have rwx----- (700) permissions. Please refer to the installation documentation for a system property that can be set to remove this restriction.	Verify that directory permissions allow RSA Identity Governance and Lifecycle to write to the directory. Alternatively, you can set a system property to remove this restriction. See "Using Non-restrictive Mode for the Encryption Key Directory" in the previous section.

Upgrade AFX

When AFX is also installed on your appliance, RSA Identity Governance and Lifecycle automatically upgrades AFX whenever you upgrade RSA Identity Governance and Lifecycle using the `-afx` option with `install.sh` (`install.sh -afx`). Otherwise, you are required to complete the tasks in this section to successfully upgrade AFX in other RSA Identity Governance and Lifecycle deployment scenarios.

Perform the tasks in this section only if you are upgrading from v6.8.1 or later. If you are upgrading from a pre-v6.8.1 version of RSA Identity Governance and Lifecycle, see [Upgrade AFX If You Have a Pre-6.8.1 Version Installed](#) for instructions.

Note: The Federated Salesforce and Microsoft Exchange connector templates have been deprecated for versions 7.0.1 and higher. On upgrade, any dependent connectors that exist would be removed from the system. You cannot import or migrate these templates or related connectors after you upgrade.

Before you begin

Perform the following before you upgrade AFX

- Stop all AFX servers.
 - Example 1: `/home/afxuser/AFX/afx stop`
 - Example 2: `/home/oracle/AFX/afx stop`
- Upgrade RSA Identity Governance and Lifecycle.

Procedure

1. Start all AFX servers:
 - a. Connect to the AFX server machine using the "afx account."
 - b. Start AFX using the "afx" admin script located in the top level AFX installation directory:


```
<path-to-AFX>/afx start
```

 - Example 1: `/home/afxuser/AFX/afx start`
 - Example 2: `/home/oracle/AFX/afx start`
2. Monitor the upgrade status.
 - To confirm the upgrade is in progress, see the `/home/oracle/AFX/esb/logs/AFX-INIT.log` file. Look for the "Initiating server upgrade" entry.
 - To view upgrade steps that have been completed and to confirm that the upgrade was successful, see the `/home/oracle/AFXServer-upgrade/afx-server-upgrade-<timestamp>.log` file. Look for the "Success" entry.
3. Download the AFX connectors and templates package for the RSA Identity Governance and Lifecycle product upgrade or patch version from RSA Link.

For example: `AFX-<product version>-Standard-Connectors.zip`
4. Log in to RSA Identity Governance and Lifecycle and do the following.

- a. From AFX > Import, select the package and import all files in the package.
- b. From AFX > Connector Templates, verify that your template versions match the RSA Identity Governance and Lifecycle product version you installed.
- c. From AFX > Connectors, verify that the status of your connectors is "Running."

For more information on working with AFX, see online Help.

Upgrade AFX If You Have a Pre-6.8.1 Version Installed

This section describes how to upgrade your existing AFX installation to version 7.x. This process consists of the following tasks:

- [Migrate AFX Connectors and Templates from AFX 2.0.x or 2.5.x](#)
- [Upgrade the AFX Server to Version 7.x](#)

Migrate AFX Connectors and Templates from AFX 2.0.x or 2.5.x

All AFX 7.x (and 2.9.x) data, including connector templates and connector files, are stored in the RSA Identity Governance and Lifecycle database. Data from versions 2.0.x and 2.5.x was stored on the AFX server machine. To load connectors and templates from these versions into the RSA Identity Governance and Lifecycle database, do the following:

1. [Run the AFX Connector Converter Utility.](#)
2. [Import the Connector and the Connector Template Packages Archives into RSA Identity Governance and Lifecycle v7.x.](#)

Run the AFX Connector Converter Utility

The Connector Package File Migration utility generates a new connector package zip file that contains the connectors and a template zip file that contains the templates. You can then import the zip files into the RSA Identity Governance and Lifecycle database.

Procedure

1. Connect to your AFX server machine as root user.
2. Stop the AFX Server if it is running.
3. Back up the existing AFX installation by copying the current AFX install directory and all of its contents. For example, if your current AFX installation is located at /opt/AFX:

```
cp -rpf /opt/AFX /opt/AFX-backup
```

4. Choose a download directory on the AFX server machine (/tmp for example).
5. Download AFX-<product-version>-Connector-Converter.zip from the packages directory for this RSA Identity Governance and Lifecycle release version.
6. Change to the download directory and expand the connector converter zip file:

```
cd /tmp
```

7. Unzip AFX-<product-version>-Connector-Converter.zip.

This creates an AFXConverter directory that includes all of the components required to run the utility.

8. Change to the AFXConverter directory and run the utility with required inputs provided for the Mule installation directory and output destination directory. The name of the Mule installation directory depends on the AFX version that is currently installed. For example, if AFX is installed in /opt/AFX and output is to be saved to /tmp/AFXConverter/output:

- For AFX 2.0.x installations:

```
cd /tmp/AFXConverter
./afx_connector_converter.sh /opt/AFX/mule-ee-3.2.1
/tmp/AFXConverter/output
```

- For AFX 2.5.x installations:

```
cd /tmp/AFXConverter
./afx_connector_converter.sh /opt/AFX/mule
/tmp/AFXConverter/output
```

9. After the utility has completed, find the following files in the output directory and copy them to a system from which you can access the RSA Identity Governance and Lifecycle application via a web browser:
 - /tmp/AFXConverter/output/AFXConnectorTypePackages.zip (contains connector templates and supporting files)
 - /tmp/AFXConverter/output/AFXConnectorPackages.zip (contains connectors and supporting files)

Import the Connector and the Connector Template Packages Archives into RSA Identity Governance and Lifecycle v7.x

After you complete the steps in [Run the AFX Connector Converter Utility](#) to generate the packages archive of your previous release, import the archive into to RSA Identity Governance and Lifecycle 7.x.

Note: The Federated Salesforce and Microsoft Exchange connector templates have been deprecated for versions 7.0.1 and higher. On upgrade, any dependent connectors that exist would be removed from the system. You cannot import or migrate these templates or related connectors after you upgrade.

Procedure

1. Log on to RSA Identity Governance and Lifecycle as an administrator user, AveksaAdmin for example.
2. Click AFX > Import.

The Import Connector Package page appears.

3. Click Browse, select the AFXConnectorTypePackages.zip file, select Select All Items and then click Next to import it.
4. Click Browse, select the AFXConnectorPackages.zip file, select and then click Next to import it.

The connector template and connector packages are loaded into the RSA Identity Governance and Lifecycle database.

5. After you have imported the packages archives, you must download and import the AFX 7.x connector packages included in the RSA Identity Governance and Lifecycle release. This step is required to migrate

your connectors and templates to ensure compatibility with an AFX 7.x server installation. See "Install the AFX Connector Packages" in the *Installation Guide*.

For security reasons, values for password settings are not included in the connector packages generated by the converter utility and thus are not populated for the connectors that were imported/migrated. You must edit each connector and update the value for any password setting after you install the connector packages.

Upgrade the AFX Server to Version 7.x

This section describes how to upgrade the AFX server to version 7.x. To upgrade your AFX server, you must first uninstall the existing AFX server version and then install version 7.x.

Procedure

1. Connect to the AFX server machine as root user.
2. Stop the AFX server if it is running.
3. Back up your existing AFX installation by copying the current AFX install directory and all contents. For example, if your current AFX installation is located at /opt/AFX:

```
cp -rpf /opt/AFX /opt/AFX-backup
```

4. Remove your existing AFX deployment:
 - If upgrading from a pre-2.8.1 version, perform the uninstall procedure documented in the *Access Fulfillment Express Guide* for the AFX server version you have currently installed. See the "Uninstall the AFX Server" section.
 - If upgrading from a 2.8.x version or greater, disable AFX from Admin > System > Settings. For more information, see *Specifying System Settings in Help*.
5. Delete the existing AFX install directory and all of its contents. For example, if your current AFX installation is located in /opt/AFX:

```
rm -rf /opt/AFX
```

6. Disconnect from the AFX server machine and follow the steps in "Installing the AFX Server" in the *Installation Guide* to install AFX Server version 7.x.

Verify the Upgrade

Services are automatically restarted after you upgrade RSA Identity Governance and Lifecycle. You are not required to start services manually.

Procedure

1. Check the upgrade log files (/tmp/aveksa-install.log) to ensure there are no problems indicated by a "Step failed" message.

The installation process involves installation of several components. Log output varies depending on whether you performed a new or upgrade installation. "Step failed" messages indicate where the problem occurred.

You can ignore the following output from the Oracle installer:

```
CRS-4000: Command Start failed, or completed with errors.
PRCR-1079 : Failed to start resource ora.asm
[WARNING] [INS-41812] OSDBA and OSASM are the same OS group.
ORA-01078: failure in processing system parameter
```

Note: For more information on system-generated error messages, see the "Troubleshooting" appendix in the *Installation Guide*.

2. Log on to RSA Identity Governance and Lifecycle and complete the following tasks:
 - Verify various screens to ensure they are functioning properly.
 - Run various tasks, such as collections, reviews, reports, and rules.

Update Keystores

After you upgrade, you must update **server.keystore** and **client.keystore** for all remote agents and AFX.

Procedure

1. Log in to RSA Identity Governance and Lifecycle, and go to **Admin > System > Security**. In a clustered environment, perform this step on the single system operations node (SON).
2. Click **Change Certificate Store**, and click **OK** to change the root certificate and CA.
3. Click **Download** and save the **server.keystore** file to a location on your computer.
4. Go to **AFX > Servers**, click **Change Certificate Store**, and click **OK** to change the client certificate.
5. Click **Download** and save the **client.keystore** file to a location on your computer.
6. Stop the ACM and AFX servers.
7. Copy the new **server.keystore** file to the location on the server where your web server reads the keystore. For example, **\$AVEKSA_HOME/keystore**.
8. Copy the new **client.keystore** file to the AFX server under **<AFX-server-root>/esb/conf**.
9. Update the client.keystore files from the remote agents after you download the corresponding client.keystore from RSA Identity Governance and Lifecycle.
10. Restart the ACM and AFX servers and verify connectivity with the endpoints.

Chapter 7: Upgrade or Migrate to an RSA Identity Governance and Lifecycle Virtual Application

Note: Virtual applications are intended to be replaced rather than upgraded within the same OVA. To upgrade an existing RSA Identity Governance and Lifecycle virtual application deployment to a new version, download the latest OVA from RSA, and complete the following procedures to migrate to the new OVA.

To migrate RSA Identity Governance and Lifecycle from a software bundle to a virtual application:

1. [Download and Install the RSA Identity Governance and Lifecycle Virtual Application OVA on page 60](#)
2. [Set Up the Database for the Virtual Application on page 61](#) (Only if you need to deploy a new database)
3. [Set Up the RSA Identity Governance and Lifecycle Virtual Application on page 61](#)
4. [Restore the RSA Identity Governance and Lifecycle Deployment on page 63](#)

Download and Install the RSA Identity Governance and Lifecycle Virtual Application OVA

RSA distributes the RSA Identity Governance and Lifecycle virtual application as an OVA file, which you download and install as a virtual application. To deploy the virtual application, you must use VMware ESXi version 5.x or higher.

Procedure

1. Go to [RSA Link](https://community.rsa.com/community/products/governance-and-lifecycle) (https://community.rsa.com/community/products/governance-and-lifecycle), then click **Log In** and enter your user name and password.
2. **Click RSA Identity Governance and Lifecycle 7.2**
3. Click **Version Upgrades**.
4. Click the **Upgrade** link for your licensed RSA Identity Governance and Lifecycle asset.
5. Click **Continue**.
6. On the Order Detail page, click the menu icon and select **Product List**.
The **Current** tab lists the most recent release or patch. The **Archive** tab lists previous releases and patches.
7. Click the appropriate tab, and select the name of the release to download.
8. Download the following files:
 - OVA: **RSA_IGL.x86_64-<VersionNumber>.ova**
 - (If you are not using a customer-supplied database) Database Installation Kit: **RSA_IGL_DatabaseOnly.tar.bz2**
9. Follow the documentation for your virtual infrastructure to install the OVA, using the following configuration settings:

Setting	Value
CPU	4 CPUs, with 1 core per socket
Memory	16 GB or greater
Hard Disk	Retain the default value

10. Power on the virtual application.

Set Up the Database for the Virtual Application

- Perform this procedure if you are creating a new database for your virtual application deployment using the database-only installer. The database must be installed on physical hardware, rather than in a virtualized environment.
- Do not perform this procedure if you are upgrading from a previous OVA and using the same database.
- If you plan to deploy your own customer-supplied database, refer to the *RSA Identity Governance and Lifecycle Database Setup and Management Guide* for requirements and instructions.

Procedure

1. Log into the database installation machine as root.

Note: You must log in as the root account to ensure that the proper permissions are granted. This procedure may not work using any other account.

2. Extract the file **RSA_IGL_DatabaseOnly.tar.bz2** to the /tmp directory using the following command:

```
tar xjf RSA_IGL_DatabaseOnly.tar.bz2
```

3. Execute the script **installDatabaseOnly.sh** using the following command:

```
./installDatabaseOnly.sh
```

When the script completes, a standalone Oracle database server is configured with the appropriate tablespace, users, and schema for RSA Identity Governance and Lifecycle. Logs are accessible in the /tmp/aveksa-install.log directory.

4. Log out of all open sessions from the root account after the installation has finished. You need to log in again to apply the environment changes to your session.

Set Up the RSA Identity Governance and Lifecycle Virtual Application

Use the RSA Identity Governance and Lifecycle virtual application setup interface to configure the virtual application. The setup interface automatically guides you through each step of the virtual application configuration.

Use the arrow keys to move between form fields, and the Tab key to select options at the bottom of each screen.

Procedure

1. Power on the virtual machine and log in as root using the standard password.

Note: You must log in as the root account to ensure that the proper permissions are granted. This procedure may not work using any other account.

2. At the prompt asking if you want to set up RSA Identity Governance and Lifecycle, use TAB to select **Yes**, and press Enter.

3. Configure the network settings for the virtual application:
 - a. On the Main Menu screen, ensure that **1 Network Setup** is selected, select **OK**, and press Enter.
 - b. On the Network Configuration screen, enter the fully qualified domain name (**FQDN**), the IPv4 or IPv6 **IP Address**, **Netmask**, and the default **Gateway** for your RSA Identity Governance and Lifecycle deployment, then select **Submit**, and press Enter.
The network automatically restarts.
 - c. At the prompt asking if you want to verify the network, select **Yes** to verify your network configuration or **No** to skip the test, and press Enter.
 - d. If you performed the network test, select **OK** after the test completes and press Enter.
4. Configure the domain name servers (DNS):
 - a. Ensure that **2 DNS Setup** is selected, select **OK**, and press Enter.
 - b. Enter the IP addresses of your DNS, select **Submit**, and press Enter.
If DNS configuration is successful, a confirmation message appears.
 - c. Select **OK** and press Enter.
5. Configure the NTP server:
 - a. Ensure that **3 NTP Setup** is selected, select **OK**, and press Enter.
 - b. Enter the IP address or hostname of your NTP server, select **Submit**, and press Enter.
A message is displayed indicating that it can take up to ten minutes to verify the NTP server connection.
 - c. Select **OK** and press Enter.
6. Configure the Oracle database as follows. If you are migrating from an older OVA, provide the same database details.
 - a. Ensure that **4 DB Setup** is selected, select **OK**, and press Enter.
 - b. Enter the following details for your deployment, if applicable:
 - Oracle Listening hostname
 - Oracle Listener port
 - Oracle SID
 - Oracle Service Name
 - Oracle Connection ID
 - Avekxa (AvekxaAdmin) user name
 - Avekxa (AvekxaAdmin) user password
 - Reports user name
 - Reports user password
 - Public db user name
 - Public db user password
 - Statspack user name
 - Statspack user password
 - c. Select **Submit**, and press Enter.
 - d. At the prompt asking if you want to verify the database connection, select **Yes** to verify that the network and database are configured correctly, or **No** to return to the main menu, and press Enter.

- e. If you performed the database connection test, on the confirmation message, click **OK**, and press Enter.
7. Configure RSA Identity Governance and Lifecycle on the virtual application:
 - a. Ensure that **5 Configure** is selected, select **OK**, and press Enter.
 - b. At the prompt asking if you want to enable the Access Fulfillment Express (AFX) service, select **YES** or **NO**, and press Enter.
The console displays details of the configuration as it is performed.
 - c. When the RSA Identity Governance and Lifecycle configuration is complete, press any key to return to the main menu.
8. (Optional) To disable the setup interface from automatically running after logging into the virtual application as root:
 - a. Select **6 Disable**, select **OK**, and press Enter.
 - b. At the confirmation message, select **Yes**, and press Enter.
9. (Optional) To display the status of the virtual application configuration:
 - a. Select **7 Status**, select **OK**, and press Enter.
The test progress is displayed as the network, NTP, and database connections are tested. When the test is complete, the test results are displayed to indicate whether items are successfully configured.
 - b. Select **OK**, and press Enter.
10. (Optional) To turn the color mode on or off for the status labels, Select **8 Turn on/off color mode**, select **OK**, and press Enter.
When color mode is enabled, the virtual application setup interface color-codes the status label for each configuration step. When disabled, the status labels appear as standard text. This option can help with status readability.

Restore the RSA Identity Governance and Lifecycle Deployment

After you deploy the virtual application, use the following procedure to restore the RSA Identity Governance and Lifecycle software from your software bundle deployment.

Procedure

1. Login to the virtual application as the root user.
2. Stop RSA Identity Governance and Lifecycle services by entering the following command:

```
service aveksa_server stop
```

3. Copy the **Backup<version>.tar** file to the following directory:

```
/home/oracle/AveksaExportImportDir
```

4. Migrate the database by entering the following command:

```
/home/oracle/deploy/migrate.sh
```

Output similar to the following appears:

...

The logs are available at: /home/oracle/upgrade/log

The DB schema migration logs available at: /home/oracle/database/log

Scanning migration logs..

Potential errors found in these log files:

Migration logs are available at the locations displayed. If there are errors shown under "Potential errors," this may indicate a problem with the migration of your database. Contact Customer Support for assistance as necessary.

5. Restart the Oracle database:

- a. Stop the database by entering the following command:

```
service aveksa_server stopdb
```

- b. Start the database by entering the following command:

```
service aveksa_server startdb
```

6. Start RSA Identity Governance and Lifecycle services by entering the following command:

```
service aveksa_server start
```

7. If you are replacing an old OVA, shut the old virtual application down to ensure that it does not appear as an additional node in your deployment.

